SPRS051H - JANUARY 1997 - REVISED MARCH 2004

- High-Performance Fixed-Point Digital Signal Processor (DSP) TMS320C6201
 - 5-ns Instruction Cycle Time
 - 200-MHz Clock Rate
 - Eight 32-Bit Instructions/Cycle
 - 1600 MIPS
- VelociTI[™] Advanced Very Long Instruction Word (VLIW) TMS320C62x[™] DSP CPU Core
 - Eight Independent Functional Units:
 - Six ALUs (32-/40-Bit)
 - Two 16-Bit Multipliers (32-Bit Results)
 - Load-Store Architecture With 32 32-Bit General-Purpose Registers
 - Instruction Packing Reduces Code Size
 - All Instructions Conditional
- Instruction Set Features
 - Byte-Addressable (8-, 16-, 32-Bit Data)
 - 32-Bit Address Range
 - 8-Bit Overflow Protection
 - Saturation
 - Bit-Field Extract, Set, Clear
 - Bit-Counting
 - Normalization
- 1M-Bit On-Chip SRAM
 - 512K-Bit Internal Program/Cache (16K 32-Bit Instructions)
 - 512K-Bit Dual-Access Internal Data (64K Bytes) Organized as Two Blocks for Improved Concurrency
- 32-Bit External Memory Interface (EMIF)
 - Glueless Interface to Asynchronous Memories: SRAM and EPROM
 - Glueless Interface to Synchronous Memories: SDRAM and SBSRAM
- Four-Channel Bootloading Direct-Memory-Access (DMA) Controller with an Auxiliary Channel
- 16-Bit Host-Port Interface (HPI)
 Access to Entire Memory Map

GJC/GJL 352-PIN BALL GRID ARRAY (BGA) PACKAGES (BOTTOM VIEW)



- Two Multichannel Buffered Serial Ports (McBSPs)
 - Direct Interface to T1/E1, MVIP, SCSA Framers
 - ST-Bus-Switching Compatible
 - Up to 256 Channels Each
 - AC97-Compatible
 - Serial Peripheral Interface (SPI) Compatible (Motorola[™])
- Two 32-Bit General-Purpose Timers
- Flexible Phase-Locked Loop (PLL) Clock Generator
- IEEE-1149.1 (JTAG[†]) Boundary-Scan Compatible
- 352-Pin BGA Package (GJC Suffix)
- 352-Pin BGA Package (GJL Suffix)
- CMOS Technology
 0.18-μm/5-Level Metal Process
- 3.3-V I/Os, 1.8-V Internal



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

VelociTI and TMS320C62x are trademarks of Texas Instruments. Motorola is a trademark of Motorola, Inc.

All other trademarks are the property of their respective owners.

[†] IEEE Standard 1149.1-1990 Standard-Test-Access Port and Boundary Scan Architecture.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.



Copyright © 2004, Texas Instruments Incorporated

SPRS051H - JANUARY 1997 - REVISED MARCH 2004

Table of Co	nte
GJC/GJL BGA packages (bottom view) 1	
description 2	
device characteristics 3	
functional and CPU (DSP core) block diagram	
CPU (DSP core) description 5	
signal groups description 7	
signal descriptions	
development support 20	
documentation support 23	
clock PLL	
power-down mode logic 25	
power-supply sequencing	
absolute maximum ratings over operating case	
temperature ranges 28	
recommended operating conditions	
electrical characteristics over recommended ranges of	
supply voltage and operating case temperature 29	

ents	
parameter measurement information 30)
input and output clocks 31	I
asynchronous memory timing 33	3
synchronous-burst memory timing 35	5
synchronous DRAM timing 39)
HOLD/HOLDA timing 43	3
reset timing 44	1
external interrupt timing 46	3
host-port interface timing 47	7
multichannel buffered serial port timing 50	נ
DMAC, timer, power-down timing 61	I
JTAG test-port timing 62	2
revision history 63	3
thermal/mechanical data 64	1

description

The TMS320C62x[™] DSPs (including the TMS320C6201[†]) are the fixed-point DSP family in the TMS320C6000[™] DSP platform. The C6201 device is based on the high-performance, advanced VelociTI[™] very-long-instruction-word (VLIW) architecture developed by Texas Instruments (TI), making these DSPs an excellent choice for multichannel and multifunction applications. With performance of up to 1600 MIPS at a clock rate of 200 MHz, the C6201 offers cost-effective solutions to high-performance DSP programming challenges. The C6201 DSP possesses the operational flexibility of high-speed controllers and the numerical capability of array processors. The processor has 32 general-purpose registers of 32-bit word length and eight highly independent functional units. The eight functional units provide six arithmetic logic units (ALUs) for a high degree of parallelism and two 16-bit multipliers for a 32-bit result. The C6201 can produce two multiply-accumulates (MACs) per cycle—for a total of 466 million MACs per second (MMACS). The C62x[™] DSP also has application-specific hardware logic, on-chip memory, and additional on-chip peripherals.

The C6201 includes a large bank of on-chip memory and has a powerful and diverse set of peripherals. Program memory consists of a 64K-byte block that is user-configurable as cache or memory-mapped program space. Data memory of the C6201 consists of two 32K-byte blocks of RAM for improved concurrency. The peripheral set includes two multichannel buffered serial ports (McBSPs), two general-purpose timers, a host-port interface (HPI), and a glueless external memory interface (EMIF) capable of interfacing to SDRAM or SBSRAM and asynchronous peripherals.

The C62x[™] DSP has a complete set of development tools which includes: a new C compiler, an assembly optimizer to simplify programming and scheduling, and a Windows[™] debugger interface for visibility into source code execution.

TMS320C6000 and C62x are trademarks of Texas Instruments.

Windows is a registered trademark of the Microsoft Corporation.

[†] The TMS320C6201 device shall be referred to as C6201 throughout the remainder of this document.



device characteristics

Table 1 provides an overview of the C6201 DSP. The table shows significant features of each device, including the capacity of on-chip RAM, the peripherals, the execution time, and the package type with pin count.

	HARDWARE FEATURES	C6201 (FIXED-POINT DSP)		
	EMIF	1		
	DMA	1		
Peripherals	HPI	1		
	McBSPs	2		
	32-Bit Timers	2		
	Size (Bytes)	72K		
On-Chip Memory	Organization	512-Kbit Program Memory 512-Kbit Data Memory (organized as two blocks)		
CPU ID+Rev ID	Control Status Register (CSR.[31:16])	0x0002		
Frequency	MHz	200		
Cycle Time	ns	5 ns (C6201-200)		
Mallana	Core (V)	1.8		
voltage	I/O (V)	3.3		
PLL Options	CLKIN frequency multiplier	Bypass (x1), x4		
RCA Deskages	27 x 27 mm	352-Pin BGA (GJL)		
DGA Packages	35 x 35 mm	352-Pin BGA (GJC)		
Process Technology	μm	0.18 μm		
Product Status	Product Preview (PP) Advance Information (AI) Production Data (PD)	PD		
Device Part Numbers	(For more details on the C6000™ DSP part numbering, see Figure 4)	TMS320C6201GJC200 TMS320C6201GJCA200 TMS320C6201GJL200 TMS320C6201GJLA200		

Table 1. Characteristics of the C6201 Processor

C6000 is a trademark of Texas Instruments.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

functional and CPU (DSP core) block diagram





CPU (DSP core) description

The CPU fetches VelociTI[™] advanced very-long instruction words (VLIW) (256 bits wide) to supply up to eight 32-bit instructions to the eight functional units during every clock cycle. The VelociTI[™] VLIW architecture features controls by which all eight units do not have to be supplied with instructions if they are not ready to execute. The first bit of every 32-bit instruction determines if the next instruction belongs to the same execute packet as the previous instruction, or whether it should be executed in the following clock as a part of the next execute packet. Fetch packets are always 256 bits wide; however, the execute packets can vary in size. The variable-length execute packets are a key memory-saving feature, distinguishing the C62x CPU from other VLIW architectures.

The CPU features two sets of functional units. Each set contains four units and a register file. One set contains functional units .L1, .S1, .M1, and .D1; the other set contains units .D2, .M2, .S2, and .L2. The two register files each contain 1632-bit registers for a total of 32 general-purpose registers. The two sets of functional units, along with two register files, compose sides A and B of the CPU [see functional and CPU (DSP core) block diagram and Figure 1]. The four functional units on each side of the CPU can freely share the 16 registers belonging to that side. Additionally, each side features a single data bus connected to all the registers on the other side, by which the two sets of functional units can access data from the register files on the opposite side. While register access by functional units on the same side of the CPU as the register file can service all the units in a single clock cycle, register access using the register file across the CPU supports one read and one write per cycle.

Another key feature of the C62x CPU is the load/store architecture, where all instructions operate on registers (as opposed to data in memory). Two sets of data-addressing units (.D1 and .D2) are responsible for all data transfers between the register files and the memory. The data address driven by the .D units allows data addresses generated from one register file to be used to load or store data to or from the other register file. The C62x CPU supports a variety of indirect addressing modes using either linear- or circular-addressing modes with 5- or 15-bit offsets. All instructions are conditional, and most can access any one of the 32 registers. Some registers, however, are singled out to support specific addressing or to hold the condition for conditional instructions (if the condition is not automatically "true"). The two .M functional units are dedicated for multiplies. The two .S and .L functional units perform a general set of arithmetic, logical, and branch functions with results available every clock cycle.

The processing flow begins when a 256-bit-wide instruction fetch packet is fetched from a program memory. The 32-bit instructions destined for the individual functional units are "linked" together by "1" bits in the least significant bit (LSB) position of the instructions. The instructions that are "chained" together for simultaneous execution (up to eight in total) compose an execute packet. A "0" in the LSB of an instruction breaks the chain, effectively placing the instructions that follow it in the next execute packet. If an execute packet crosses the fetch packet boundary (256 bits wide), the assembler places it in the next fetch packet, while the remainder of the current fetch packet is padded with NOP instructions. The number of execute packets within a fetch packet can vary from one to eight. Execute packets are dispatched to their respective functional units at the rate of one per clock cycle and the next 256-bit fetch packet is not fetched until all the execute packets from the current fetch packet have been dispatched. After decoding, the instructions simultaneously drive all active functional units for a maximum execution rate of eight instructions every clock cycle. While most results are stored in 32-bit registers, they can be subsequently moved to memory as bytes or half-words as well. All load and store instructions are byte-, half-word, or word-addressable.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

CPU (DSP core) description (continued)







SPRS051H - JANUARY 1997 - REVISED MARCH 2004



signal groups description





SPRS051H - JANUARY 1997 - REVISED MARCH 2004

signal groups description (continued)



Figure 3. Peripheral Signals



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

Signal Descriptions								
SIGNAL	PIN NO.			DECODIDION				
NAME	GJC	GJL	ITPE'	DESCRIPTION				
CLOCK/PLL								
CLKIN	C10	B9	I	Clock Input				
CLKOUT1	AF22	AC18	0	Clock output at full device speed				
CLKOUT2	AF20	AC16	0	Clock output at half of device speed				
CLKMODE1	C6	D8		Clock mode selects				
CLKMODE0	C5	C7	1	For more details on the GJC and GJL CLKMODE pins and the PLL multiply factors, see the <i>Clock PLL</i> section of this data sheet.				
PLLFREQ3	A9	A9		PLL frequency range (3, 2, and 1)				
PLLFREQ2	D11	D11	I	The target range for CLKOUT1 frequency is determined by the 3-bit value of the				
PLLFREQ1	B10	B10		PLLFREQ pins.				
PLLV [‡]	D12	B11	A§	PLL analog V_{CC} connection for the low-pass filter				
PLLG [‡]	C12	C12	A§	PLL analog GND connection for the low-pass filter				
PLLF	A11	D12	A§	PLL low-pass filter connection to external components and a bypass capacitor				
				JTAG EMULATION				
TMS	L3	L3	I	JTAG test port mode select (features an internal pullup)				
TDO	W2	U4	O/Z	JTAG test port data out				
TDI	R4	T2	I	JTAG test port data in (features an internal pullup)				
ТСК	R3	R3	I	JTAG test port clock				
TRST	T1	R4	I	JTAG test port reset (features an internal pulldown)				
EMU1	Y1	V3	I/O/Z	Emulation pin 1, pullup with a dedicated 20-k Ω resistor [¶]				
EMU0	W3	W2	I/O/Z	Emulation pin 0, pullup with a dedicated 20-k Ω resistor [¶]				
			•	RESET AND INTERRUPTS				
RESET	K2	K2	I	Device reset				
NMI	L2	L2	I	Nonmaskable interrupt				
				Edge-driven (rising edge)				
EXT_INT7	U3	U2	-	External interrupts				
EXT_INT6	V2	T4		Edge-driven				
EXT_INT5	W1	V1		Polarity independently selected via the external interrupt polarity register bits				
EXT_INT4	U4	V2		(EXTPOL.[3:0])				
IACK	Y2	Y1	0	Interrupt acknowledge for all active interrupts serviced by the CPU				
INUM3	AA1	V4	1	Active interrunt identification number				
INUM2	W4	Y2	0					
INUM1	AA2	AA1	Ŭ	Fince during IACK for all active interrupts (not just external) Fince during order follows the interrupt-service fetch-packet ordering				
INUM0	AB1	W4						
				LITTLE ENDIAN/BIG ENDIAN				
LENDIAN	H3	G2	I	If high, LENDIAN selects little-endian byte/half-word addressing order within a word If low, LENDIAN selects big-endian addressing				
				POWER-DOWN STATUS				
PD	D3	E2	0	Power-down mode 2 or 3 (active if high)				

[†] I = Input, O = Output, Z = High Impedance, S = Supply Voltage, GND = Ground

[‡] PLLV and PLLG are not part of external voltage supply or ground. See the *clock PLL* section for information on how to connect these pins.

§ A = Analog Signal (PLL Filter)

[¶] For emulation and normal operation, pull up EMU1 and EMU0 with a dedicated 20-kΩ resistor. For boundary scan, pull down EMU1 and EMU0 with a dedicated 20-kΩ resistor.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

Signal Descriptions (Continued)									
SIGNAL	PIN NO.		T/05+	DECODIDION					
NAME	GJC	GJL	TTPE	DESCRIPTION					
HOST-PORT INTERFACE (HPI)									
HINT	H26	J26	0	Host interrupt (from DSP to host)					
HCNTL1	F23	G24	I	Host control - selects between control, address, or data registers					
HCNTL0	D25	F25	I	Host control - selects between control, address, or data registers					
HHWIL	C26	E26	I	Host half-word select - first or second half-word (not necessarily high or low order)					
HBE1	E23	F24	I	Host byte select within word or half-word					
HBE0	D24	E25	I	Host byte select within word or half-word					
HR/W	C23	B22	I	Host read or write select					
HD15	B13	A12							
HD14	B14	D13							
HD13	C14	C13							
HD12	B15	D14							
HD11	D15	B15							
HD10	B16	C15							
HD9	A17	D15		Host-port data (used for transfer of data, address, and control)					
HD8	B17	B16	1/0/7						
HD7	D16	C16	1/0/2						
HD6	B18	B17							
HD5	A19	D16							
HD4	C18	A18							
HD3	B19	B18							
HD2	C19	D17							
HD1	B20	C18							
HD0	B21	A20							
HAS	C22	C20	I	Host address strobe					
HCS	B23	B21	I	Host chip select					
HDS1	D22	C21	I	Host data strobe 1					
HDS2	A24	D20	I	Host data strobe 2					
HRDY	J24	J25	0	Host ready (from DSP to host)					
				BOOT MODE					
BOOTMODE4	D8	C8							
BOOTMODE3	B4	B6]						
BOOTMODE2	A3	D7	I	Boot mode					
BOOTMODE1	D5	C6							
BOOTMODE0	C4	B5							

 † I = Input, O = Output, Z = High Impedance, S = Supply Voltage, GND = Ground



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

SIGNAL	PIN N	10.	T/05+	DESCRIPTION						
NAME	GJC	GJL	ITPE'	DESCRIPTION						
	EMIF - CONTROL SIGNALS COMMON TO ALL TYPES OF MEMORY									
CE3	AE22	AD20								
CE2	AD26	AA24	0/7	Memory space enables						
CE1	AB24	AB26	0,2	 Consistent of the second address Only one asserted during any external data access 						
CE0	AC26	AA25								
BE3	AB25	Y24		Byte-enable control						
BE2	AA24	W23		C Decoded from the two lowest bits of the internal address						
BET	Y23	AA26	0/Z	Byte-write enables for most types of memory						
BEO	AA26	W25		Can be directly connected to SDRAM read and write mask signal (SDQM)						
				EMIF - ADDRESS						
EA21	J26	K25								
EA20	K25	L24								
EA19	L24	L25								
EA18	K26	M23								
EA17	M26	M25								
EA16	M25	M24								
EA15	P25	N23								
EA14	P24	P24								
EA13	R25	P23								
EA12	T26	R25								
EA11	R23	R24	O/Z	External address (word address)						
EA10	U26	R23								
EA9	U25	T25								
EA8	T23	T24								
EA7	V26	U25								
EA6	V25	T23								
EA5	W26	V26	1							
EA4	V24	V25	1							
EA3	W25	U23	1							
EA2	Y26	V24	1							

Signal Descriptions (Continued)



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

Signal Descriptions (Continued)									
SIGNAL	PIN N	10.		DESCRIPTION					
NAME	GJC	GJL	ITPE'	DESCRIPTION					
EMIF - DATA									
ED31	AB2	Y3							
ED30	AC1	AA2							
ED29	AA4	AB1							
ED28	AD1	AA3							
ED27	AC3	AB2							
ED26	AD4	AE5							
ED25	AF3	AD6							
ED24	AE4	AC7							
ED23	AD5	AE6							
ED22	AF4	AD7							
ED21	AE5	AC8							
ED20	AD6	AD8							
ED19	AE6	AC9							
ED18	AD7	AF7							
ED17	AC8	AD9							
ED16	AF7	AC10	107	Z External data					
ED15	AD9	AE9	1/0/2						
ED14	AD10	AF9							
ED13	AF9	AC11							
ED12	AC11	AE10							
ED11	AE10	AD11							
ED10	AE11	AE11							
ED9	AF11	AC12							
ED8	AE14	AD12							
ED7	AF15	AE12							
ED6	AE15	AC13							
ED5	AF16	AD14							
ED4	AC15	AC14							
ED3	AE17	AE15							
ED2	AF18	AD15							
ED1	AF19	AE16							
ED0	AC17	AD16							
	•		EMIF - A	ASYNCHRONOUS MEMORY CONTROL					
ARE	Y24	V23	O/Z	Asynchronous memory read enable					
AOE	AC24	AB25	O/Z	Asynchronous memory output enable					
AWE	AD23	AE22	O/Z	Asynchronous memory write enable					
ARDY	W23	Y26	I	Asynchronous memory ready input					



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

SIGNAL	PIN NO.			DESCRIPTION					
NAME	GJC	GJL	ITPE'	DESCRIPTION					
EMIF - SYNCHRONOUS BURST SRAM (SBSRAM) CONTROL									
SSADS	AC20	AD19	O/Z	SBSRAM address strobe					
SSOE	AF21	AD18	O/Z	SBSRAM output enable					
SSWE	AD19	AF18	O/Z	SBSRAM write enable					
SSCLK	AD17	AC15	0	SBSRAM clock					
		E	MIF - SY	NCHRONOUS DRAM (SDRAM) CONTROL					
SDA10	AD21	AC19	O/Z	SDRAM address 10 (separate for deactivate command)					
SDRAS	AF24	AD21	O/Z	SDRAM row-address strobe					
SDCAS	AD22	AC20	O/Z	SDRAM column-address strobe					
SDWE	AF23	AE21	O/Z	SDRAM write enable					
SDCLK	AE20	AC17	0	SDRAM clock					
				EMIF - BUS ARBITRATION					
HOLD	AA25	Y25	I	Hold request from the host					
HOLDA	A7	C9	0	Hold-request acknowledge to the host					
				TIMER1					
TOUT1	H24	K23	0	Timer 1 or general-purpose output					
TINP1	K24	L23	I	Timer 1 or general-purpose input					
				TIMERO					
TOUTO	M4	M4	0	Timer 0 or general-purpose output					
TINP0	K4	H2	I	Timer 0 or general-purpose input					
			D	MA ACTION COMPLETE STATUS					
DMAC3	D2	E1							
DMAC2	F4	F2							
DMAC1	D1	G3	0	DMA action complete					
DMAC0	E2	H4							
		MU	LTICHAN	NEL BUFFERED SERIAL PORT 1 (McBSP1)					
CLKS1	E25	F26	I	External clock source (as opposed to internal)					
CLKR1	H23	H25	I/O/Z	Receive clock					
CLKX1	F26	J24	I/O/Z	Transmit clock					
DR1	D26	H23	I	Receive data					
DX1	G23	G25	O/Z	Transmit data					
FSR1	E26	J23	I/O/Z	Receive frame sync					
FSX1	F25	G26	I/O/Z	Transmit frame sync					

Signal Descriptions (Continued)



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

Signal Descriptions (Continued)

SIGNAL	PIN NO.			
NAME	GJC	GJL	TYPE	DESCRIPTION
		MU	LTICHAN	NEL BUFFERED SERIAL PORT 0 (McBSP0)
CLKS0	L4	L4	I	External clock source (as opposed to internal)
CLKR0	M2	M2	I/O/Z	Receive clock
CLKX0	L1	M3	I/O/Z	Transmit clock
DR0	J1	J1	I	Receive data
DX0	R1	P4	O/Z	Transmit data
FSR0	P4	N3	I/O/Z	Receive frame sync
FSX0	P3	N4	I/O/Z	Transmit frame sync
	-		-	RESERVED FOR TEST
RSV0	T2	Т3	I	Reserved for testing, pullup with a dedicated 20-k Ω resistor
RSV1	G2	F1	I	Reserved for testing, pullup with a dedicated 20-k Ω resistor
RSV2	C11	C11	I	Reserved for testing, pullup with a dedicated 20-k Ω resistor
RSV3	B9	D10	I	Reserved for testing, pullup with a dedicated 20-k Ω resistor
RSV4	A6	D9	I	Reserved for testing, <i>pulldown</i> with a dedicated 20-k Ω resistor
RSV5	C8	A7	0	Reserved (leave unconnected, <i>do not</i> connect to power or ground)
RSV6	C21	D18	I	Reserved for testing, pullup with a dedicated 20-k Ω resistor
RSV7	B22	C19	I	Reserved for testing, pullup with a dedicated 20-k Ω resistor
RSV8	A23	D19	I	Reserved for testing, pullup with a dedicated 20-k Ω resistor
RSV9	E4	F3	0	Reserved (leave unconnected, <i>do not</i> connect to power or ground)
				UNCONNECTED PINS
	A8	AF20		
	B8	AE18		
	C9	AE17		
	D10	-		
	D21	-		
NC	G1	J4		Unconnected pins
	H1	J3		
	H2	G1		
	J2	K4]	
	K3	J2		
	R2	R2		



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

SIGNAL	PIN N	10.	e.g.	
NAME	GJC	GJL	TYPE [†]	DESCRIPTION
				I 3.3-V SUPPLY VOLTAGE PINS
	A10	A5		
	A15	A11		
	A18	A16		
	A21	A22		
	A22	B7		
	B7	B8		
	C1	B19		
	D17	B20		
	F3	C10		
	G24	C14		
	G25	C17		
	H25	G4		
	J25	G23		
	L25	H3		
	M3	H24		
	N3	K3		
	N23	K24	S	
	R26	L1		
	T24	L26		
	U24	N24		3.3.V supply voltage
DVDD	W24	P3		0.5-v supply voltage
	Y4	T1		
	AB3	T26		
	AB4	U3		
	AB26	U24		
	AC6	W3		
	AC10	W24		
	AC19	Y4		
	AC21	Y23		
	AC22	AD10		
	AC25	AD13		
	AD11	AD17		
	AD13	AE7		
	AD15	AE8		
	AD18	AE19		
	AE18	AE20		
	AE21	AF5		
	AF5	AF11		
	AF6	AF16		
	AF17	AF22		

Signal Descriptions (Continued)



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

Signal Descriptions (Continued)										
SIGNAL	PIN	10.		DESCRIPTION						
NAME	GJC	GJL	ITPE	DESCRIPTION						
1.8-V SUPPLY VOLTAGE PINS										
	A5	A1								
	A12	A2								
	A16	A3								
	A20	A24								
	B2	A25								
	B6	A26								
	B11	B1								
	B12	B2								
	B25	B3								
	C3	B24								
	C15	B25								
	C20	B26								
	C24	C1								
	D4	C2								
	D6	C3								
	D7	C4								
	D9	C23								
	D14	C24		1.8-V supply voltage						
	D18	C25								
CV _{DD}	D20	C26	S							
	D23	D3								
	E1	D4								
	F1	D5								
	H4	D22								
	J4	D23								
	J23	D24								
	K1	E4								
	K23	E23								
	M1	AB4								
	M24	AB23								
	N4	AC3								
	N25	AC4								
	P2	AC5								
	P23	AC22								
	Т3	AC23								
	T4	AC24	1							
	U1	AD1								
	V4	AD2	1							



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

	Signal Descriptions (Continued)						
SIGNAL	PIN N	10.	TYPE [†]	DESCRIPTION			
NAME	GJC	GJL					
			1.8-V S	UPPLY VOLTAGE PINS (CONTINUED)			
	V23	AD3					
	AC4	AD4					
	AC9	AD23					
	AC12	AD24	1				
	AC13	AD25					
	AC18	AD26					
l .	AC23	AE1	1				
	AD3	AE2					
CVnn	AD8	AE3	s	1.8-V supply voltage			
	AD14	AE24					
	AD24	AE25					
	AE2	AE26					
	AE8	A⊢1					
	AE12	A⊦2					
	AE25	A⊢3					
	AF12	AF24					
	-	AF25					
	-	AF26	<u> </u>				
		<u> </u>	1	GROUND PINS			
	A1	A4	4				
	AZ	A0	4				
	A4	Að					
· ·	A13	A10	1				
· ·	A14 A25	A13	1				
· ·	A20	A14	1				
· ·	AZU B1	A15	1				
· ·	Ba	A17 A10	1				
	B5	A19 A01					
VSS	B01	A21	GND	Ground pins			
· ·	D24 B26	R/	1				
	62	B12					
	02	B13	1				
	C13	B14					
·	C16	B23					
	C17	C5					
	C25	C22					
	D13	D1					

Signal Descriptions (Continued)



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

			Sigr	nal Descriptions (Continued)
SIGNAL	PIN N	10.	TVDET	DESCRIPTION
NAME	GJC	GJL	1166.	BESCHIFTION
				GROUND PINS (CONTINUED)
	D19	D2		
	E3	D6		
	E24	D21		
	F2	D25		
	F24	D26		
	G3	E3		
	G4	E24		
	G26	F4		
	J3	F23		
	L23	H1		
	L26	H26		
	M23	K1		
	N1	K26		
	N2	M1		
	N24	M26		
	N26	N1		
	P1	N2		
	P26	N25		
<i>,</i>	R24	N26		
VSS	T25	P1	GND	Ground pins
	U2	P2		
	U23	P25		
	V1	P26		
	V3	R1		
	Y3	R26		
	Y25	U1		
	AA3	U26		
	AA23	W1		
	AB23	W26		
	AC2	AA4		
	AC5	AA23		
	AC7	AB3		
	AC14	AB24		
	AC16	AC1		
	AD2	AC2		
	AD12	AC6		
	AD16	AC21	1	
	AD20	AC25	1	



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

			eig.		
SIGNAL	PIN N	10.		DECODIDION	
NAME	GJC	GJL	ITPE'	DESCRIPTION	
				GROUND PINS (CONTINUED)	
	AD25	AC26			
	AE1	AD5			
	AE3	AD22			
	AE7	AE4			
	AE9	AE13			
	AE13	AE14			
	AE16	AE23			
	AE19	AF4	1		
	AE23	AF6			
V _{SS}	AE24	AF8	GND	Ground pins	
	AE26	AF10	1		
	AF1	AF12	1		
	AF2	AF13	1		
	AF8	AF14	1		
	AF10	AF15	1		
	AF13	AF17	1		
	AF14	AF19]		
	AF25	AF21	1		
	AF26	AF23	1		

Signal Descriptions (Continued)



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

development support

TI offers an extensive line of development tools for the TMS320C6000[™] DSP platform, including tools to evaluate the performance of the processors, generate code, develop algorithm implementations, and fully integrate and debug software and hardware modules.

The following products support development of C6000[™] DSP-based applications:

Software Development Tools:

Code Composer Studio[™] Integrated Development Environment (IDE) including Editor C/C++/Assembly Code Generation, and Debug plus additional development tools Scalable, Real-Time Foundation Software (DSP BIOS), which provides the basic run-time target software needed to support any DSP application.

Hardware Development Tools:

Extended Development System (XDS[™]) Emulator (supports C6000[™] DSP multiprocessor system debug) EVM (Evaluation Module)

The *TMS320* DSP Development Support Reference Guide (SPRU011) contains information about development-support products for all TMS320[™] DSP family member devices, including documentation. See this document for further information on TMS320[™] DSP documentation or any TMS320[™] DSP support products from Texas Instruments. An additional document, the *TMS320 Third-Party* Support Reference Guide (SPRU052), contains information about TMS320[™] DSP-related products from other companies in the industry. To receive TMS320[™] DSP literature, contact the Literature Response Center at 800/477-8924.

For a complete listing of development-support tools for the TMS320C6000[™] DSP platform, visit the Texas Instruments web site on the Worldwide Web at http://www.ti.com uniform resource locator (URL) and under "Development Tools", select "Digital Signal Processors". For information on pricing and availability, contact the nearest TI field sales office or authorized distributor.

Code Composer Studio, XDS, and TMS320 are trademarks of Texas Instruments.



device and development-support tool nomenclature

To designate the stages in the product development cycle, TI assigns prefixes to the part numbers of all TMS320 DSP devices and support tools. Each TMS320 DSP commerical family member has one of three prefixes: TMX, TMP, or TMS. Texas Instruments recommends two of three possible prefix designators for support tools: TMDX and TMDS. These prefixes represent evolutionary stages of product development from engineering prototypes (TMX/TMDX) through fully qualified production devices/tools (TMS/TMDS).

Device development evolutionary flow:

- **TMX** Experimental device that is not necessarily representative of the final device's electrical specifications
- **TMP** Final silicon die that conforms to the device's electrical specifications but has not completed quality and reliability verification
- TMS Fully qualified production device

Support tool development evolutionary flow:

- **TMDX** Development-support product that has not yet completed Texas Instruments internal qualification testing.
- TMDS Fully qualified development-support product

TMX and TMP devices and TMDX development-support tools are shipped against the following disclaimer:

"Developmental product is intended for internal evaluation purposes."

TMS devices and TMDS development-support tools have been characterized fully, and the quality and reliability of the device have been demonstrated fully. TI's standard warranty applies.

Predictions show that prototype devices (TMX or TMP) have a greater failure rate than the standard production devices. Texas Instruments recommends that these devices not be used in any production system because their expected end-use failure rate still is undefined. Only qualified production devices are to be used.

TI device nomenclature also includes a suffix with the device family name. This suffix indicates the package type (for example, GJC or GJL), the temperature range (for example, blank is the default commercial temperature range), and the device speed range in megahertz (for example, -200 is 200 MHz). Figure 4 provides a legend for reading the complete device name for any TMS320C6000 DSP family member.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

device and development-support tool nomenclature (continued)



[†] BGA = Ball Grid Array

Figure 4. TMS320C6000 Device Nomenclature (Including TMS320C6201)

MicroStar BGA is a trademark of Texas Instruments.



documentation support

Extensive documentation supports all TMS320 DSP family devices from product announcement through applications development. The types of documentation available include: data sheets, such as this document, with design specifications; complete user's reference guides for all devices and tools; technical briefs; development-support tools; on-line help; and hardware and software applications. The following is a brief, descriptive list of support documentation specific to the C6000 DSP devices:

The *TMS320C6000 CPU and Instruction Set Reference Guide* (literature number SPRU189) describes the C6000 CPU (DSP core) architecture, instruction set, pipeline, and associated interrupts.

The *TMS320C6000 DSP Peripherals Overview Reference Guide* (literature number SPRU190) briefly describes the functionality of the peripherals available on the C6000[™] DSP platform of devices, such as the 64-/32-/16-bit external memory interfaces (EMIFs), 32-/16-bit host-port interfaces (HPIs), multichannel buffered serial ports (McBSPs), direct memory access (DMA), enhanced direct-memory-access (EDMA) controller, expansion bus (XB), peripheral component interconnect (PCI), clocking and phase-locked loop (PLL); and power-down modes.

The *TMS320C6000 Technical Brief* (literature number SPRU197) gives an introduction to the C62x/C67x[™] devices, associated development tools, and third-party support.

The tools support documentation is electronically available within the Code Composer Studio[™] IDE. For a complete listing of the latest C6000[™] DSP documentation, visit the Texas Instruments web site on the Worldwide Web at http://www.ti.com uniform resource locator (URL).



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

clock PLL

All of the C62x clocks are generated from a single source through the CLKIN pin. This source clock either drives the PLL, which generates the internal CPU clock, or bypasses the PLL to become the CPU clock.

To use the PLL to generate the CPU clock, the filter circuit shown in Figure 5 must be properly designed. Note that for C6201, the EMI filter must be powered by the I/O voltage (3.3 V).

To configure the C62x PLL clock for proper operation, see Figure 5 and Table 2. To minimize the clock jitter, a single clean power supply should power both the C62x DSP device and the external clock oscillator circuit. The minimum CLKIN rise and fall times should also be observed. See the *input and output clocks* section for input clock timing requirements.



- NOTES: A. Keep the lead length and the number of vias between pin PLLF, pin PLLG, R1, C1, and C2 to a minimum. In addition, place all PLL components (R1, C1, C2, C3, C4, and EMI Filter) as close to the C6000[™] DSP device as possible. Best performance is achieved with the PLL components on a single side of the board without jumpers, switches, or components other than the ones shown. For CLKMODE x4, values for C1, C2, and R1 are fixed and apply to all valid frequency ranges of CLKIN and CLKOUT.
 - B. For CLKMODE x1, the PLL is bypassed and all six external PLL components can be removed. For this case, the PLLV terminal has to be connected to a clean supply and the PLLG and PLLF terminals should be tied together.
 - C. Due to overlap of frequency ranges when choosing the PLLFREQ, more than one frequency range can contain the CLKOUT1 frequency. Choose the lowest frequency range that includes the desired frequency. For example, for CLKOUT1 = 133 MHz, a PLLFREQ value of 000b should be used. For CLKOUT1 = 200 MHz, PLLFREQ should be set to 001b. PLLFREQ values other than 000b, 001b, and 010b are reserved.
 - D. The 3.3-V supply for the EMI filter (and PLLV) must be from the same 3.3-V power plane supplying the I/O voltage, DV_{DD}.
 - E. EMI filter manufacturer TDK part number ACF451832-153-T

Figure 5. PLL Block Diagram



clock PLL (continued)

CLKMODE	CLKIN RANGE (MHz)	CPU CLOCK FREQUENCY (CLKOUT1) RANGE (MHz)	CLKOUT2 RANGE (MHz)	R1 (Ω)	C1 (nF)	C2 (pF)	TYPICAL LOCK TIME (μs) [†]
x4	12.5-50	50-200	25-100	60.4	27	560	75

Table 2. PLL Component Selection Table

[†] Under some operating conditions, the maximum PLL lock time may vary as much as 150% from the specified typical value. For example, if the typical lock time is specified as 100 μs, the maximum value may be as long as 250 μs.

power-down mode logic

Figure 6 shows the power-down mode logic on the C6201.





triggering, wake-up, and effects

The power-down modes and their wake-up methods are programmed by setting the PWRD field (bits 15-10) of the control status register (CSR). The PWRD field of the CSR is shown in Figure 7 and described in Table 3. When writing to the CSR, all bits of the PWRD field should be set at the same time. Logic 0 should be used when "writing" to the reserved bit (bit 15) of the PWRD field. The CSR is discussed in detail in the *TMS320C6000 CPU and Instruction Set Reference Guide* (literature number SPRU189).



SPRS051H - JANUARY 1997 - REVISED MARCH 2004



Legend: R/W-x = Read/write reset value

NOTE: The shadowed bits are not part of the power-down logic discussion and therefore are not covered here. For information on these other bit fields in the CSR register, see the *TMS320C6000 CPU and Instruction Set Reference Guide* (literature number SPRU189).

Figure 7. PWRD Field of the CSR Register

Power-down mode PD1 takes effect eight to nine clock cycles after the instruction that sets the PWRD bits in the CSR.

If PD1 mode is terminated by a non-enabled interrupt, the program execution returns to the instruction where PD1 took effect. If PD1 mode is terminated by an enabled interrupt, the interrupt service routine will be executed first, then the program execution returns to the instruction where PD1 took effect. The GIE bit in CSR and the NMIE bit in the interrupt enable register (IER) must also be set in order for the interrupt service routine to execute; otherwise, execution returns to the instruction where PD1 took effect upon PD1 mode termination by an enabled interrupt.

PD2 and PD3 modes can only be aborted by device reset. Table 3 summarizes all the power-down modes.



PRWD FIELD (BITS 15-10)	POWER-DOWN MODE	WAKE-UP METHOD	EFFECT ON CHIP'S OPERATION
000000	No power-down	—	—
001001	PD1	Wake by an enabled interrupt	CPU halted (except for the interrupt logic) Power-down mode blocks the internal clock inputs at the
010001	PD1	Wake by an enabled or non-enabled interrupt	boundary of the CPU, preventing most of the CPU's logic from switching. During PD1, DMA transactions can proceed between peripherals and internal memory.
011010	PD2 [†]	Wake by a device reset	Output clock from PLL is halted, stopping the internal clock structure from switching and resulting in the entire chip being halted. All register and internal RAM contents are preserved. All functional I/O "freeze" in the last state when the PLL clock is turned off.
011100	PD3†	Wake by a device reset	Input clock to the PLL stops generating clocks. All register and internal RAM contents are preserved. All functional I/O "freeze" in the last state when the PLL clock is turned off. Following reset, the PLL needs time to re-lock, just as it does following power-up. Wake-up from PD3 takes longer than wake-up from PD2 because the PLL needs to be re-locked.
All others	Reserved		

Table 3. Characteristics of the Power-Down Modes

[†] When entering PD2 and PD3, all functional I/O remains in the previous state. However, for peripherals which are asynchronous in nature or peripherals with an external clock source, output signals may transition in response to stimulus on the inputs. Under these conditions, peripherals will not operate according to specifications.

power-supply sequencing

TI DSPs do not require specific power sequencing between the core supply and the I/O supply. However, systems should be designed to ensure that neither supply is powered up for extended periods of time if the other supply is below the proper operating voltage.

system-level design considerations

System-level design considerations, such as bus contention, may require supply sequencing to be implemented. In this case, the core supply should be powered up at the same time as, or prior to (and powered down after), the I/O buffers. This is to ensure that the I/O buffers receive valid inputs from the core before the output buffers are powered up, thus, preventing bus contention with other chips on the board.

power-supply design considerations

For systems using the C6000 DSP platform of devices, the core supply may be required to provide in excess of 2 A per DSP until the I/O supply is powered up. This extra current condition is a result of uninitialized logic within the DSP(s) and is corrected once the CPU sees an internal clock pulse. With the PLL enabled, as the I/O supply is powered on, a clock pulse is produced stopping the extra current draw from the supply. With the PLL disabled, an external clock pulse may be required to stop this extra current draw. A normal current state returns once the I/O power supply is turned on and the CPU sees a clock pulse. Decreasing the amount of time between the core supply power up and the I/O supply power up can minimize the effects of this current draw.

A dual-power supply with simultaneous sequencing, such as available with TPS563xx controllers or PT69xx plug-in power modules, can be used to eliminate the delay between core and I/O power up [see the *Using the TPS56300 to Power DSPs Application Report* (literature number SLVA088)]. A Schottky diode can also be used to tie the core rail to the I/O rail, effectively pulling up the I/O power supply to a level that can help initialize the logic within the DSP.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

Core and I/O supply voltage regulators should be located close to the DSP (or DSP array) to minimize inductance and resistance in the power delivery path. Additionally, when designing for high-performance applications utilizing the C6000 platform of DSPs, the PC board should include separate power planes for core, I/O, and ground, all bypassed with high-quality low-ESL/ESR capacitors.

absolute maximum ratings over operating case temperature ranges (unless otherwise noted)[†]

Supply voltage range, CV _{DD} (see Note 1)	0.3 V to 2.3 V
Supply voltage range, DV _{DD} (see Note 1)	0.3 V to 4 V
Input voltage range	0.3 V to 4 V
Output voltage range	0.3 V to 4 V
Operating case temperature ranges T _C : (default)	$\ldots~0^\circ C$ to $90^\circ C$
(A version)	-40°C to 105°C
Storage temperature range, T _{stg}	-65°C to 150°C

[†] Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTE 1: All voltage values are with respect to V_{SS.}

recommended operating conditions

			MIN	NOM	MAX	UNIT	
$\rm CV_{\rm DD}$	Supply voltage			1.8	1.89	V	
DV_DD	Supply voltage		3.14	3.30	3.46	V	
$V_{\rm SS}$	Supply ground	el input voltage			0	V	
V_{IH}	igh-level input voltage					V	
V_{IL}	w-level input voltage				0.8	V	
I _{OH}	High-level output current				-12	mA	
I _{OL}	Low-level output current	Low-level output current			12	mA	
-		Default	0		90		
1C	A version				105	10	



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

electrical characteristics over recommended ranges of supply voltage and operating case temperature (unless otherwise noted)

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
V _{OH}	High-level output voltage	$DV_{DD} = MIN,$ $I_{OH} = MAX$	2.4			V
V _{OL}	Low-level output voltage	DV _{DD} = MIN, I _{OL} = MAX			0.6	V
I _I	Input current [‡]	$V_{I} = V_{SS}$ to DV_{DD}			±10	uA
I _{OZ}	Off-state output current	$V_{O} = DV_{DD}$ or 0 V			±10	uA
I _{DD2V}	Supply current, CPU + CPU memory access§	CV _{DD} = NOM, CPU clock = 167 MHz		380		mA
I _{DD2V}	Supply current, peripherals [§]	CV _{DD} = NOM, CPU clock = 167 MHz		240		mA
I _{DD3V}	Supply current, I/O pins [§]	DV _{DD} = NOM, CPU clock = 167 MHz		90		mA
Ci	Input capacitance				10	pF
Co	Output capacitance				10	pF

[‡] TMS and TDI are not included due to internal pullups. TRST is not included due to internal pulldown.

§ Measured with average activity (50% high / 50% low power). For more details on CPU, peripheral, and I/O activity, see the TMS320C6000 Power Consumption Summary application report (literature number SPRA486).



SPRS051H - JANUARY 1997 - REVISED MARCH 2004



Figure 8. TTL-Level Outputs

signal transition levels

All input and output timing parameters are referenced to 1.5 V for both "0" and "1" logic levels.



Figure 9. Input and Output Voltage Reference Levels for AC Timing Measurements

All rise and fall transition timing parameters are referenced to V_{IL} MAX and V_{IH} MIN for input clocks, and V_{OL} MAX and V_{OH} MIN for output clocks.



Figure 10. Rise and Fall Transition Time Voltage Reference Levels



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

INPUT AND OUTPUT CLOCKS

timing requirements for CLKIN^{†‡} (see Figure 11)

			-200				
NO.			CLKM = >	ODE (4	CLKM0 = x1	DDE I	UNIT
			MIN	MAX	MIN	MAX	
1	t _{c(CLKIN)}	Cycle time, CLKIN	20		5		ns
2	t _{w(CLKINH)}	Pulse duration, CLKIN high	0.4C		0.45C		ns
3	t _{w(CLKINL)}	Pulse duration, CLKIN low	0.4C		0.45C		ns
4	t _{t(CLKIN)}	Transition time, CLKIN		5		0.6	ns

 † The reference points for the rise and fall transitions are measured at V_{\rm IL} MAX and V_{\rm IH} MIN.

[‡] C = CLKIN cycle time in ns. For example, when CLKIN frequency is 50 MHz, use C = 20 ns.



Figure 11. CLKIN Timings

switching characteristics over recommended operating conditions for CLKOUT1§1# (see Figure 12)

NO.	PARAMETER			DE = X4	CLKMO	UNIT	
			MIN	MAX	MIN	MAX	
1	t _{c(CKO1)}	Cycle time, CLKOUT1	P - 0.7	P + 0.7	P - 0.7	P + 0.7	ns
2	t _{w(CKO1H)}	Pulse duration, CLKOUT1 high	(P/2) - 0.5	(P/2) + 0.5	PH - 0.5	PH + 0.5	ns
3	t _{w(CKO1L)}	Pulse duration, CLKOUT1 low	(P/2) - 0.5	(P/2) + 0.5	PL - 0.5	PL + 0.5	ns
4	t _{t(CKO1)}	Transition time, CLKOUT1		0.6		0.6	ns

P = 1/CPU clock frequency in ns.

[¶] The reference points for the rise and fall transitions are measured at V_{OL} MAX and V_{OH} MIN. [#] PH is the high period of CLKIN in ns and PL is the low period of CLKIN in ns.



Figure 12. CLKOUT1 Timings



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

INPUT AND OUTPUT CLOCKS (CONTINUED)

switching characteristics over recommended operating conditions for CLKOUT2^{†‡} (see Figure 13)

		-2			
NO.			MIN	MAX	UNIT
1	t _{c(CKO2)}	Cycle time, CLKOUT2	2P - 0.7	2P + 0.7	ns
2	t _{w(CKO2H)}	Pulse duration, CLKOUT2 high	P - 0.7	P + 0.7	ns
3	t _{w(CKO2L)}	Pulse duration, CLKOUT2 low	P - 0.7	P + 0.7	ns
4	t _{t(CKO2)}	Transition time, CLKOUT2		0.6	ns

[†] P = 1/CPU clock frequency in ns.

 ‡ The reference points for the rise and fall transitions are measured at V_{OL} MAX and V_{OH} MIN.



Figure 13. CLKOUT2 Timings

SDCLK, SSCLK timing parameters

SDCLK timing parameters are the same as CLKOUT2 parameters.

SSCLK timing parameters are the same as CLKOUT1 or CLKOUT2 parameters, depending on SSCLK configuration.

switching characteristics over recommended operating conditions for the relation of SSCLK, SDCLK, and CLKOUT2 to CLKOUT1 (see Figure 14)[†]

		-2			
NO.		MIN	MAX	UNIT	
1	t _{d(CKO1-SSCLK)}	Delay time, CLKOUT1 edge to SSCLK edge	(P/2) + 0.2	(P/2) + 4.2	ns
2	t _{d(CKO1-SSCLK1/2)}	Delay time, CLKOUT1 edge to SSCLK edge (1/2 clock rate)	(P/2) - 1	(P/2) + 2.4	ns
3	t _{d(CKO1-CKO2)}	Delay time, CLKOUT1 edge to CLKOUT2 edge	(P/2) - 1	(P/2) + 2.4	ns
4	t _{d(CKO1-SDCLK)}	Delay time, CLKOUT1 edge to SDCLK edge	(P/2) - 1	(P/2) + 2.4	ns

[†] P = 1/CPU clock frequency in ns.





SPRS051H - JANUARY 1997 - REVISED MARCH 2004

ASYNCHRONOUS MEMORY TIMING

timing requirements for asynchronous memory cycles[†] (see Figure 15 and Figure 16)

			-200		LINUT
NO.					
6	t _{su(EDV-CKO1H)}	Setup time, read EDx valid before CLKOUT1 high	4		ns
7	t _{h(CKO1H-EDV)}	Hold time, read EDx valid after CLKOUT1 high	0.8		ns
10	t _{su(ARDY-CKO1H)}	Setup time, ARDY valid before CLKOUT1 high	3		ns
11	t _{h(CKO1H-ARDY)}	Hold time, ARDY valid after CLKOUT1 high	1.8		ns

[†] To ensure data setup time, simply program the strobe width wide enough. ARDY is internally synchronized. If ARDY does meet setup or hold time, it may be recognized in the current cycle or the next cycle. Thus, ARDY can be an asynchronous input.

switching characteristics over recommended operating conditions for asynchronous memory cycles[‡] (see Figure 15 and Figure 16)

NO		PARAMETER		-200		
NO.				MAX	UNIT	
1	t _{d(CKO1H-CEV)}	Delay time, CLKOUT1 high to CEx valid	-0.2	4	ns	
2	t _{d(CKO1H-BEV)}	Delay time, CLKOUT1 high to BEx valid		4	ns	
3	t _{d(CKO1H-BEIV)}	Delay time, CLKOUT1 high to BEx invalid	-0.2		ns	
4	t _{d(CKO1H-EAV)}	Delay time, CLKOUT1 high to EAx valid		4	ns	
5	t _{d(CKO1H-EAIV)}	Delay time, CLKOUT1 high to EAx invalid	-0.2		ns	
8	t _{d(CKO1H-AOEV)}	Delay time, CLKOUT1 high to AOE valid	-0.2	4	ns	
9	t _{d(CKO1H-AREV)}	Delay time, CLKOUT1 high to ARE valid	-0.2	4	ns	
12	t _{d(CKO1H-EDV)}	Delay time, CLKOUT1 high to EDx valid		4	ns	
13	t _{d(CKO1H-EDIV)}	Delay time, CLKOUT1 high to EDx invalid	-0.2		ns	
14	t _{d(CKO1H-AWEV)}	Delay time, CLKOUT1 high to AWE valid	-0.2	4	ns	

[‡] The minimum delay is also the minimum output hold after CLKOUT1 high.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004



ASYNCHRONOUS MEMORY TIMING (CONTINUED)









SPRS051H - JANUARY 1997 - REVISED MARCH 2004

SYNCHRONOUS-BURST MEMORY TIMING

timing requirements for synchronous-burst SRAM cycles (full-rate SSCLK) (see Figure 17)

			-2	-200	
NO.			MIN	N MAX	UNIT
7	t _{su(EDV-SSCLKH)}	Setup time, read EDx valid before SSCLK high	1.5		ns
8	t _{h(SSCLKH-EDV)}	Hold time, read EDx valid after SSCLK high	1.5		ns

switching characteristics over recommended operating conditions for synchronous-burst SRAM cycles[†] (full-rate SSCLK) (see Figure 17 and Figure 18)

		DADAMETED		
NO.		PARAMETER	MIN MAX	UNIT
1	t _{osu(CEV-SSCLKH)}	Output setup time, CEx valid before SSCLK high	0.5P - 1.3	ns
2	t _{oh(SSCLKH-CEV)}	Output hold time, CEx valid after SSCLK high	0.5P - 2.3	ns
3	t _{osu(BEV-SSCLKH)}	Output setup time, BEx valid before SSCLK high	0.5P - 1.3	ns
4	t _{oh(SSCLKH-BEIV)}	Output hold time, BEx invalid after SSCLK high	0.5P - 2.3	ns
5	t _{osu(EAV-SSCLKH)}	Output setup time, EAx valid before SSCLK high	0.5P - 1.3	ns
6	t _{oh(SSCLKH-EAIV)}	Output hold time, EAx invalid after SSCLK high	0.5P - 2.3	ns
9	t _{osu(ADSV-SSCLKH)}	Output setup time, SSADS valid before SSCLK high	0.5P - 1.3	ns
10	t _{oh(SSCLKH-ADSV)}	Output hold time, SSADS valid after SSCLK high	0.5P - 2.3	ns
11	t _{osu(OEV-SSCLKH)}	Output setup time, SSOE valid before SSCLK high	0.5P - 1.3	ns
12	t _{oh(SSCLKH-OEV)}	Output hold time, SSOE valid after SSCLK high	0.5P - 2.3	ns
13	t _{osu(EDV-SSCLKH)}	Output setup time, EDx valid before SSCLK high	0.5P - 1.3	ns
14	t _{oh(SSCLKH-EDIV)}	Output hold time, EDx invalid after SSCLK high	0.5P - 2.3	ns
15	t _{osu(WEV-SSCLKH)}	Output setup time, SSWE valid before SSCLK high	0.5P - 1.3	ns
16	t _{oh(SSCLKH-WEV)}	Output hold time, SSWE valid after SSCLK high	0.5P - 2.3	ns

[†] When the PLL is used (CLKMODE x4), P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns. For CLKMODE x1, 0.5P is defined as PH (pulse duration of CLKIN high) for all output setup times; 0.5P is defined as PL (pulse duration of CLKIN low) for all output hold times.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004



SYNCHRONOUS-BURST MEMORY TIMING (CONTINUED)









SPRS051H - JANUARY 1997 - REVISED MARCH 2004

SYNCHRONOUS-BURST MEMORY TIMING (CONTINUED)

timing requirements for synchronous-burst SRAM cycles (half-rate SSCLK) (see Figure 19)

			-2	-200	
NO.			MIN	MIN MAX	UNII
7	t _{su(EDV-SSCLKH)}	Setup time, read EDx valid before SSCLK high	2.5		ns
8	t _{h(SSCLKH-EDV)}	Hold time, read EDx valid after SSCLK high	1.5		ns

switching characteristics over recommended operating conditions for synchronous-burst SRAM cycles[†] (half-rate SSCLK) (see Figure 19 and Figure 20)

	DADAMETED		-200	-200	
NO.		PARAMETER	MIN	MAX	UNIT
1	t _{osu(CEV-SSCLKH)}	Output setup time, CEx valid before SSCLK high	1.5P - 3		ns
2	t _{oh(SSCLKH-CEV)}	Output hold time, CEx valid after SSCLK high	0.5P - 1.5		ns
3	t _{osu(BEV-SSCLKH)}	Output setup time, BEx valid before SSCLK high	1.5P - 3		ns
4	t _{oh} (SSCLKH-BEIV)	Output hold time, BEx invalid after SSCLK high	0.5P - 1.5		ns
5	t _{osu(EAV-SSCLKH)}	Output setup time, EAx valid before SSCLK high	1.5P - 3		ns
6	t _{oh} (SSCLKH-EAIV)	Output hold time, EAx invalid after SSCLK high	0.5P - 1.5		ns
9	t _{osu(ADSV-SSCLKH)}	Output setup time, SSADS valid before SSCLK high	1.5P - 3		ns
10	t _{oh(SSCLKH-ADSV)}	Output hold time, SSADS valid after SSCLK high	0.5P - 1.5		ns
11	t _{osu(OEV-SSCLKH)}	Output setup time, SSOE valid before SSCLK high	1.5P - 3		ns
12	t _{oh(SSCLKH-OEV)}	Output hold time, SSOE valid after SSCLK high	0.5P - 1.5		ns
13	t _{osu(EDV-SSCLKH)}	Output setup time, EDx valid before SSCLK high	1.5P - 3		ns
14	t _{oh} (SSCLKH-EDIV)	Output hold time, EDx invalid after SSCLK high	0.5P - 1.5		ns
15	t _{osu(WEV-SSCLKH)}	Output setup time, SSWE valid before SSCLK high	1.5P - 3		ns
16	t _{oh(SSCLKH-WEV)}	Output hold time, SSWE valid after SSCLK high	0.5P - 1.5		ns

[†] When the PLL is used (CLKMODE x4), P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns. For CLKMODE x1:

1.5P = P + PH, where P = 1/CPU clock frequency, and PH = pulse duration of CLKIN high.

0.5P = PL, where PL = pulse duration of CLKIN low.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004



SYNCHRONOUS-BURST MEMORY TIMING (CONTINUED)









SPRS051H - JANUARY 1997 - REVISED MARCH 2004

SYNCHRONOUS DRAM TIMING

timing requirements for synchronous DRAM cycles (see Figure 21)

		-200			
NO.			MIN	N MAX	UNIT
7	t _{su(EDV-SDCLKH)}	Setup time, read EDx valid before SDCLK high	0.5		ns
8	t _{h(SDCLKH-EDV)}	Hold time, read EDx valid after SDCLK high	3		ns

switching characteristics over recommended operating conditions for synchronous DRAM cycles † (see Figure 21-Figure 26)

				-200	
NO.		MIN	MAX	UNIT	
1	t _{osu(CEV-SDCLKH)}	Output setup time, CEx valid before SDCLK high	1.5P - 3.5		ns
2	t _{oh(SDCLKH-CEV)}	Output hold time, CEx valid after SDCLK high	0.5P - 1		ns
3	t _{osu(BEV-SDCLKH)}	Output setup time, BEx valid before SDCLK high	1.5P - 3.5		ns
4	t _{oh(SDCLKH-BEIV)}	Output hold time, BEx invalid after SDCLK high	0.5P - 1		ns
5	t _{osu(EAV-SDCLKH)}	Output setup time, EAx valid before SDCLK high	1.5P - 3.5		ns
6	t _{oh(SDCLKH-EAIV)}	Output hold time, EAx invalid after SDCLK high	0.5P - 1		ns
9	t _{osu(SDCAS-SDCLKH)}	Output setup time, SDCAS valid before SDCLK high	1.5P - 3.5		ns
10	t _{oh(SDCLKH-SDCAS)}	Output hold time, SDCAS valid after SDCLK high	0.5P - 1		ns
11	t _{osu(EDV-SDCLKH)}	Output setup time, EDx valid before SDCLK high	1.5P - 3.5		ns
12	t _{oh(SDCLKH-EDIV)}	Output hold time, EDx invalid after SDCLK high	0.5P - 1		ns
13	t _{osu(SDWE-SDCLKH)}	Output setup time, SDWE valid before SDCLK high	1.5P - 3.5		ns
14	t _{oh(SDCLKH-SDWE)}	Output hold time, SDWE valid after SDCLK high	0.5P - 1		ns
15	t _{osu(SDA10V-SDCLKH)}	Output setup time, SDA10 valid before SDCLK high	1.5P - 3.5		ns
16	t _{oh(SDCLKH-SDA10IV)}	Output hold time, SDA10 invalid after SDCLK high	0.5P - 1		ns
17	t _{osu(SDRAS-SDCLKH)}	Output setup time, SDRAS valid before SDCLK high	1.5P - 3.5		ns
18	t _{oh(SDCLKH-SDRAS)}	Output hold time, SDRAS valid after SDCLK high	0.5P - 1		ns

[†] When the PLL is used (CLKMODE x4), P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns. For CLKMODE x1:

1.5P = P + PH, where P = 1/CPU clock frequency, and PH = pulse duration of CLKIN high.

0.5P = PL, where PL = pulse duration of CLKIN low.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004













SPRS051H - JANUARY 1997 - REVISED MARCH 2004



SYNCHRONOUS DRAM TIMING (CONTINUED)









SPRS051H - JANUARY 1997 - REVISED MARCH 2004



SYNCHRONOUS DRAM TIMING (CONTINUED)





SPRS051H - JANUARY 1997 - REVISED MARCH 2004

HOLD/HOLDA TIMING

timing requirements for the HOLD/HOLDA cycles[†] (see Figure 27)

NO		-200			
NO.			MIN	MAX	UNIT
1	t _{su(HOLDH-CKO1H)}	Setup time, HOLD high before CLKOUT1 high	1		ns
2	t _{h(CKO1H-HOLDL)}	Hold time, HOLD low after CLKOUT1 high	4		ns

[†] HOLD is synchronized internally. Therefore, if setup and hold times are not met, it will either be recognized in the current cycle or in the next cycle. Thus, HOLD can be an asynchronous input.

switching characteristics over recommended operating conditions for the HOLD/HOLDA cycles[‡] (see Figure 27)

NO.		PARAMETER			
3	t _{d(HOLDL-BHZ)}	Delay time, HOLD low to EMIF Bus high impedance	4P	ş	ns
4	t _{d(BHZ-HOLDAL)}	Delay time, EMIF Bus high impedance to HOLDA low	Р	2P	ns
5	t _{d(HOLDH-HOLDAH)}	Delay time, HOLD high to HOLDA high	4P	7P	ns
6	t _{d(CKO1H-HOLDAL)}	Delay time, CLKOUT1 high to HOLDA valid	1	8	ns
7	t _{d(CKO1H-BHZ)}	Delay time, CLKOUT1 high to EMIF Bus high impedance [¶]	3	11	ns
8	t _d (CKO1H-BLZ)	Delay time, CLKOUT1 high to EMIF Bus low impedance [¶]	3	11	ns
9	t _{d(HOLDH-BLZ)}	Delay time, HOLD high to EMIF Bus low impedance	3P	6P	ns

 ‡ P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

§ All pending EMIF transactions are allowed to complete before HOLDA is asserted. The worst cases for this is an asynchronous read or write with external ARDY used or a minimum of eight consecutive SDRAM reads or writes when RBTR8 = 1. If no bus transactions are occurring, then the minimum delay time can be achieved. Also, bus hold can be indefinitely delayed by setting NOHOLD = 1.

* EMIF Bus consists of CE[3:0], BE[3:0], ED[31:0], EA[21:2], ARE, AOE, AWE, SSADS, SSOE, SSWE, SDA10, SDRAS, SDCAS, and SDWE.



[†] EMIF Bus consists of CE[3:0], BE[3:0], ED[31:0], EA[21:2], ARE, AOE, AWE, SSADS, SSOE, SSWE, SDA10, SDRAS, SDCAS, and SDWE.

Figure 27. HOLD/HOLDA Timing



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

RESET TIMING

timing requirements for reset (see Figure 28)

				00	
NO.			MIN	MAX	UNIT
1	t _{w(RST)}	Width of the \overrightarrow{RESET} pulse (PLL stable) [†]	10		CLKOUT1 cycles
		Width of the \overrightarrow{RESET} pulse (PLL needs to sync up) [‡]	250		μs

[†] This parameter applies to CLKMODE x1 when CLKIN is stable and applies to CLKMODE x4 when CLKIN and PLL are stable.

[‡] This parameter only applies to CLKMODE x4. The RESET signal is not connected internally to the clock PLL circuit. The PLL, however, may need up to 250 μs to stabilize following device power up or after PLL configuration has been changed. During that time, RESET must be asserted to ensure proper device operation. See the *Clock PLL* section for PLL lock times.

switching characteristics over recommended operating conditions during reset^{§¶} (see Figure 28)

				00	LINUT
NO.		PARAMETER	MIN	MAX	UNIT
2	t _{R(RST)}	Response time to change of value in RESET signal	2		CLKOUT1 cycles
3	t _{d(CKO1H-CKO2IV)}	Delay time, CLKOUT1 high to CLKOUT2 invalid	-1		ns
4	t _{d(CKO1H-CKO2V)}	Delay time, CLKOUT1 high to CLKOUT2 valid		10	ns
5	t _{d(CKO1H-SDCLKIV)}	Delay time, CLKOUT1 high to SDCLK invalid	-1		ns
6	t _{d(CKO1H-SDCLKV)}	Delay time, CLKOUT1 high to SDCLK valid		10	ns
7	t _{d(CKO1H-SSCKIV)}	Delay time, CLKOUT1 high to SSCLK invalid	-1		ns
8	t _{d(CKO1H-SSCKV)}	Delay time, CLKOUT1 high to SSCLK valid		10	ns
9	t _{d(CKO1H-LOWIV)}	Delay time, CLKOUT1 high to low group invalid	-1		ns
10	t _{d(CKO1H-LOWV)}	Delay time, CLKOUT1 high to low group valid		10	ns
11	t _{d(CKO1H-HIGHIV)}	Delay time, CLKOUT1 high to high group invalid	-1		ns
12	t _{d(CKO1H-HIGHV)}	Delay time, CLKOUT1 high to high group valid		10	ns
13	t _{d(CKO1H-ZHZ)}	Delay time, CLKOUT1 high to Z group high impedance	-1		ns
14	t _{d(CKO1H-ZV)}	Delay time, CLKOUT1 high to Z group valid		10	ns

 § Low group consists of:
 IACK, INUM[3:0], DMAC[3:0], PD, TOUT0, and TOUT1

 High group consists of:
 HINT

 Z group consists of:
 EA[21:2], ED[31:0], CE[3:0], BE[3:0], ARE, AWE, AOE, SS

EA[21:2], ED[31:0], CE[3:0], BE[3:0], ARE, AWE, AOE, SSADS, SSOE, SSWE, SDA10, SDRAS, SDCAS, SDWE, HD[15:0], CLKX0, CLKX1, FSX0, FSX1, DX0, DX1, CLKR0, CLKR1, FSR0, and FSR1.

[¶] HRDY is gated by input HCS.

If $\overline{\text{HCS}} = 0$ at device reset, $\overline{\text{HRDY}}$ belongs to the high group.

If $\overline{HCS} = 1$ at device reset, \overline{HRDY} belongs to the low group.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004



RESET TIMING (CONTINUED)

[‡] HRDY is gated by input HCS.

If HCS = 0 at device reset, HRDY belongs to the high group.

If HCS = 1 at device reset, HRDY belongs to the low group.

Figure 28. Reset Timing



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

EXTERNAL INTERRUPT TIMING

timing requirements for interrupt response cycles^{†‡} (see Figure 29)

	NO		-200		
NO.		MIN	MAX	UNIT	
2	t _{w(ILOW)} Width of the interrupt pulse low	2P		ns	
3	t _{w(IHIGH)} Width of the interrupt pulse high	2P		ns	

[†] Interrupt signals are synchronized internally and are potentially recognized one cycle later if setup and hold times are violated. Thus, they can be connected to asynchronous inputs.

 ‡ P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

switching characteristics over recommended operating conditions during interrupt response cycles[§] (see Figure 29)

NO.	DADAMETED		-20	LINUT	
		PARAMETER	MIN	MAX	UNIT
1	t _{d(EINTH-IACKH)}	Delay time, EXT_INTx high to IACK high	9P		ns
4	t _{d(CKO2L-IACKV)}	Delay time, CLKOUT2 low to IACK valid	-4	6	ns
5	t _{d(CKO2L-INUMV)}	Delay time, CLKOUT2 low to INUMx valid		6	ns
6	t _{d(CKO2L-INUMIV)}	Delay time, CLKOUT2 low to INUMx invalid	-4		ns

P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

When the PLL is used (CLKMODE x4), $0.5P = 1/(2 \times CPU \text{ clock frequency})$.

For CLKMODE x1: 0.5P = PH, where PH is the high period of CLKIN.



Figure 29. Interrupt Timing



HOST-PORT INTERFACE TIMING

timing requiremer	nts for host-por	t interface	cycles ^{†‡}	(see	Figure 30,	Figure 31,	Figure 32,	and
Figure 33)								

			-20	00	
NO.			MIN	MAX	UNIT
1	t _{su(SEL-HSTBL)}	Setup time, select signals [§] valid before HSTROBE low	4		ns
2	t _{h(HSTBL-SEL)}	Hold time, select signals [§] valid after HSTROBE low	2		ns
3	t _{w(HSTBL)}	Pulse duration, HSTROBE low	2P		ns
4	t _{w(HSTBH)}	Pulse duration, HSTROBE high between consecutive accesses	2P		ns
10	t _{su(SEL-HASL)}	Setup time, select signals [§] valid before HAS low	4		ns
11	t _{h(HASL-SEL)}	Hold time, select signals ${}^{\$}$ valid after \overline{HAS} low	2		ns
12	t _{su(HDV-HSTBH)}	Setup time, host data valid before HSTROBE high	3		ns
13	t _{h(HSTBH-HDV)}	Hold time, host data valid after HSTROBE high	2		ns
14	t _{h(HRDYL-HSTBL)}	Hold time, HSTROBE low after HRDY low. HSTROBE shoul not be inactivated until HRDY is active (low); otherwise, HPI writes will not complete properly.	1		ns
18	t _{su(HASL-HSTBL)}	Setup time, HAS low before HSTROBE low	2		ns
19	t _{h(HSTBL-HASL)}	Hold time, HAS low after HSTROBE low	2		ns

[†] HSTROBE refers to the following logical operation on HCS, HDS1, and HDS2: [NOT(HDS1 XOR HDS2)] OR HCS.

[‡] The effects of internal clock jitter are included at test. There is no need to adjust timing numbers for internal clock jitter. P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

§ Select signals include: HCNTRL[1:0], HR/W, and HHWIL.

switching characteristics over recommended operating conditions during host-port interface cycles^{†‡} (see Figure 30, Figure 31, Figure 32, and Figure 33)

NO			-2		
NO.		PARAMETER	MIN	MAX	UNIT
5	t _{d(HCS-HRDY)}	Delay time, HCS to HRDY [¶]	1	9	ns
6	t _{d(HSTBL-HRDYH)}	Delay time, HSTROBE low to HRDY high#	3	12	ns
7	t _{oh(HSTBL-HDLZ)}	Output hold time, HD low impedance after HSTROBE low for an HPI read	4		ns
8	t _{d(HDV-HRDYL)}	Delay time, HD valid to HRDY low	P - 3	P + 3	ns
9	t _{oh(HSTBH-HDV)}	Output hold time, HD valid after HSTROBE high	2	12	ns
15	t _{d(HSTBH-HDHZ)}	Delay time, HSTROBE high to HD high impedance	3	12	ns
16	t _{d(HSTBL-HDV)}	Delay time, HSTROBE low to HD valid	2	12	ns
17	t _{d(HSTBH-HRDYH)}	Delay time, HSTROBE high to HRDY high	3	12	ns
20	t _{d(HASL-HRDYH)}	Delay time, HAS low to HRDY high	3	12	ns

[†] HSTROBE refers to the following logical operation on HCS, HDS1, and HDS2: [NOT(HDS1 XOR HDS2)] OR HCS.

[‡] The effects of internal clock jitter are included at test. There is no need to adjust timing numbers for internal clock jitter. P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

¹ HCS enables HRDY, and HRDY is always low when HCS is high. The case where HRDY goes high when HCS falls indicates that HPI is busy completing a previous HPID write or READ with autoincrement.

[#] This parameter is used during an HPID read. At the beginning of the first half-word transfer on the falling edge of HSTROBE, the HPI sends the request to the DMA auxiliary channel, and HRDY remains high until the DMA auxiliary channel loads the requested data into HPID.

This parameter is used after the second half-word of an HPID write or autoincrement read. HRDY remains low if the access is not an HPID write or autoincrement read. Reading or writing to HPIC or HPIA does not affect the HRDY signal.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004



HOST-PORT INTERFACE TIMING (CONTINUED)

[†] HSTROBE refers to the following logical operation on HCS, HDS1, and HDS2: [NOT(HDS1 XOR HDS2)] OR HCS.





Figure 31. HPI Read Timing (HAS Used)



SPRS051H - JANUARY 1997 - REVISED MARCH 2004



HOST-PORT INTERFACE TIMING (CONTINUED)

[†] HSTROBE refers to the following logical operation on HCS, HDS1, and HDS2: [NOT(HDS1 XOR HDS2)] OR HCS.

Figure 32. HPI Write Timing (HAS Not Used, Tied High)



[†] HSTROBE refers to the following logical operation on HCS, HDS1, and HDS2: [NOT(HDS1 XOR HDS2)] OR HCS.

Figure 33. HPI Write Timing (HAS Used)

SPRS051H - JANUARY 1997 - REVISED MARCH 2004

MULTICHANNEL BUFFERED SERIAL PORT TIMING

timing requirements for McBSP^{†‡}(see Figure 34)

				-20	00	
NO.				MIN	MAX	UNIT
2	t _{c(CKRX)}	Cycle time, CLKR/X	CLKR/X ext	2P [§]		ns
3	t _{w(CKRX)}	Pulse duration, CLKR/X high or CLKR/X low	CLKR/X ext	P - 1 [¶]		ns
_			CLKR int	9		
5	^t su(FRH-CKRL)	Setup time, external FSR high before CLKR low	CLKR ext	2		ns
6			CLKR int	6		
	^I h(CKRL-FRH)	Hold time, external FSR high after CLKR low	CLKR ext	3		ns
-		Ontro time DD velid before OLKD law	CLKR int	8		
1	^t su(DRV-CKRL)	Setup time, DR valid before CLKR low	CLKR ext	0		ns
_			CLKR int	3		
8	^t h(CKRL-DRV)	Hold time, DR valid after CLKR low	CLKR ext	4		ns
40			CLKX int	9		
10	t _{su(FXH-CKXL)}	XL) Setup time, external FSX high before CLKX low	CLKX ext	2		ns
		(CKXL-FXH) Hold time, external FSX high after CLKX low	CLKX int	6		
	^t h(CKXL-FXH)		CLKX ext	3		ns

[†] CLKRP = CLKXP = FSRP = FSXP = 0. If polarity of any of the signals is inverted, then the timing references of that signal are also inverted. [‡] P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

[§] The maximum bit rate for the C6202/02B/03 device is 100 Mbps or CPU/2 (the slower of the two). Care must be taken to ensure that the AC timings specified in this data sheet are met. The maximum bit rate for McBSP-to-McBSP communications is 100 MHz; therefore, the minimum CLKR/X clock cycle is either twice the CPU cycle time (2P), or 10 ns (100 MHz), whichever value is larger. For example, when running parts at 200 MHz (P = 5 ns), use 10 ns as the minimum CLKR/X clock cycle (by setting the appropriate CLKGDV ratio or external clock source). When running parts at 100 MHz (P = 10 ns), use 2P = 20 ns (50 MHz) as the minimum CLKR/X clock cycle. The maximum bit rate for McBSP-to-McBSP communications applies when the serial port is a master of the clock and frame syncs (with CLKR connected to CLKX, FSR connected to FSX, CLKXM = FSXM = 1, and CLKRM = FSRM = 0) in data delay 1 or 2 mode (R/XDATDLY = 01b or 10b) and the other device the McBSP communicates to is a slave.

[¶] The minimum CLKR/X pulse duration is either (P-1) or 4 ns, whichever is larger. For example, when running parts at 200 MHz (P = 5 ns), use 4 ns as the minimum CLKR/X pulse duration. When running parts at 100 MHz (P = 10 ns), use (P-1) = 9 ns as the minimum CLKR/X pulse duration.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

MULTICHANNEL BUFFERED SERIAL PORT TIMING (CONTINUED)

switching characteristics over recommended operating conditions for McBSP^{†‡§} (see Figure 34)

		DADAMETED				
NO.		PARAMETER		MIN	MAX	UNIT
1	t _{d(CKSH-CKRXH)}	Delay time, CLKS high to CLKR/X high for internal CLKR/X generated from CLKS input		3	10	ns
2	t _{c(CKRX)}	Cycle time, CLKR/X	CLKR/X int	2P [¶]		ns
3	t _{w(CKRX)}	Pulse duration, CLKR/X high or CLKR/X low	CLKR/X int	C - 1.3 [#]	C + 1 [#]	ns
4	t _{d(CKRH-FRV)}	Delay time, CLKR high to internal FSR valid	CLKR int	-2	3	ns
9	t _{d(CKXH-FXV)}	XH-FXV) Delay time, CLKX high to internal FSX valid	CLKX int	-2	3	ns
			CLKX ext	3	9	
10		Disable time, DX high impedance following last data bit from CKXH-DXHZ) CLKX high	CLKX int	-1	4	
12	^t dis(CKXH-DXHZ)		CLKX ext	3	9	ns
10			CLKX int	-1	4	
13	^t d(CKXH-DXV)	Delay time, CLKX high to DX valid	CLKX ext	3	9	ns
	^t d(FXH-DXV)	Delay time, FSX high to DX valid	FSX int	-1	3	
14		ONLY applies when in data delay 0 (XDATDLY = 00b) mode	FSX ext	3	9	ns

[†] CLKRP = CLKXP = FSRP = FSXP = 0. If polarity of any of the signals is inverted, then the timing references of that signal are also inverted. [‡] Minimum delay times also represent minimum output hold times.

§ P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

[¶] The maximum bit rate for the C6202/02B/03 device is 100 Mbps or CPU/2 (the slower of the two). Care must be taken to ensure that the AC timings specified in this data sheet are met. The maximum bit rate for McBSP-to-McBSP communications is 100 MHz; therefore, the minimum CLKR/X clock cycle is either twice the CPU cycle time (2P), or 10 ns (100 MHz), whichever value is larger. For example, when running parts at 200 MHz (P = 5 ns), use 10 ns as the minimum CLKR/X clock cycle (by setting the appropriate CLKGDV ratio or external clock source). When running parts at 100 MHz (P = 10 ns), use 2P = 20 ns (50 MHz) as the minimum CLKR/X clock cycle. The maximum bit rate for McBSP-to-McBSP communications applies when the serial port is a master of the clock and frame syncs (with CLKR connected to CLKX, FSR connected to FSX, CLKXM = FSXM = 1, and CLKRM = FSRM = 0) in data delay 1 or 2 mode (R/XDATDLY = 01b or 10b) and the other device the McBSP communicates to is a slave.

 $^{\#}C = H \text{ or } L$

- S = sample rate generator input clock = P if CLKSM = 1 (P = 1/CPU clock frequency)
 - = sample rate generator input clock = P_clks if CLKSM = 0 (P_clks = CLKS period)

- = (CLKGDV + 1)/2 * S if CLKGDV is odd or zero
- L = CLKX low pulse width
- = (CLKGDV/2) * S if CLKGDV is even = (CLKGDV + 1)/2 * S if CLKGDV is odd or zero

POST OFFICE BOX 1443 • HOUSTON, TEXAS 77251-1443

SPRS051H - JANUARY 1997 - REVISED MARCH 2004



MULTICHANNEL BUFFERED SERIAL PORT TIMING (CONTINUED)





SPRS051H - JANUARY 1997 - REVISED MARCH 2004

MULTICHANNEL BUFFERED SERIAL PORT TIMING (CONTINUED)

timing requirements for FSR when GSYNC = 1 (see Figure 35)

		-20	-200		
NO.		MIN	MAX	UNIT	
1	t _{su(FRH-CKSH)} Setup time, FSR high before CLKS high	4		ns	
2	t _{h(CKSH-FRH)} Hold time, FSR high after CLKS high	4		ns	



Figure 35. FSR Timing When GSYNC = 1



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

MULTICHANNEL BUFFERED SERIAL PORT TIMING (CONTINUED)

timing requirements for McBSP as SPI master or slave: CLKSTP = 10b, CLKXP = 0^{++} (see Figure 36)

				-2	200		
NO.			MAS	TER	SLA	VE	UNIT
			MIN	MAX	MIN	MAX	
4	t _{su(DRV-CKXL)}	Setup time, DR valid before CLKX low	12		2 - 3P		ns
5	t _{h(CKXL-DRV)}	Hold time, DR valid after CLKX low	4		5 + 6P		ns

[†] P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

[‡] For all SPI slave modes, CLKG is programmed as 1/2 of the CPU clock by setting CLKSM = CLKGDV = 1.

switching characteristics over recommended operating conditions for McBSP as SPI master or slave: CLKSTP = 10b, CLKXP = $0^{\dagger \ddagger}$ (see Figure 36)

NO.		PARAMETER	MAS	TER§	SL	UNIT	
			MIN	MAX	MIN	MAX	
1	t _{h(CKXL-FXL)}	Hold time, FSX low after CLKX low ¶	T - 2	T + 3			ns
2	t _{d(FXL-CKXH)}	Delay time, FSX low to CLKX high [#]	L - 2	L + 3			ns
3	t _{d(CKXH-DXV)}	Delay time, CLKX high to DX valid	-2	4	3P + 4	5P + 17	ns
6	t _{dis(CKXL-DXHZ)}	Disable time, DX high impedance following last data bit from CLKX low	L - 2	L + 3			ns
7	t _{dis(FXH-DXHZ)}	Disable time, DX high impedance following last data bit from FSX high			P + 3	3P + 17	ns
8	t _{d(FXL-DXV)}	Delay time, FSX low to DX valid			2P + 2	4P + 17	ns

[†] P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

[‡] For all SPI slave modes, CLKG is programmed as 1/2 of the CPU clock by setting CLKSM = CLKGDV = 1.

§ S = sample rate generator input clock = P if CLKSM = 1 (P = 1/CPU clock frequency)

= sample rate generator input clock = P_clks if CLKSM = 0 (P_clks = CLKS period)

T = CLKX period = (1 + CLKGDV) * S

H = CLKX high pulse width = (CLKGDV/2 + 1) * S if CLKGDV is even

= (CLKGDV + 1)/2 * S if CLKGDV is odd or zero

- L = CLKX low pulse width = (CLKGDV/2) * S if CLKGDV is even
 - = (CLKGDV + 1)/2 * S if CLKGDV is odd or zero

[¶] FSRP = FSXP = 1. As a SPI master, FSX is inverted to provide active-low slave-enable output. As a slave, the active-low signal input on FSX and FSR is inverted before being used internally.

CLKXM = FSXM = 1, CLKRM = FSRM = 0 for master McBSP

CLKXM = CLKRM = FSXM = FSRM = 0 for slave McBSP

[#] FSX should be low before the rising edge of clock to enable slave devices and then begin a SPI transfer at the rising edge of the master clock (CLKX).



SPRS051H - JANUARY 1997 - REVISED MARCH 2004









SPRS051H - JANUARY 1997 - REVISED MARCH 2004

MULTICHANNEL BUFFERED SERIAL PORT TIMING (CONTINUED)

timing requirements for McBSP as SPI master or slave: CLKSTP = 11b, CLKXP = 0^{†‡} (see Figure 37)

				-2	200		
NO.			MAS	ΓER	SLA	/E	UNIT
			MIN	MAX	MIN	MAX	
4	t _{su(DRV-CKXH)}	Setup time, DR valid before CLKX high	12		2 - 3P		ns
5	t _{h(CKXH-DRV)}	Hold time, DR valid after CLKX high	4		5 + 6P		ns

[†] P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

 $^{\pm}$ For all SPI slave modes, CLKG is programmed as 1/2 of the CPU clock by setting CLKSM = CLKGDV = 1.

switching characteristics over recommended operating conditions for McBSP as SPI master or slave: CLKSTP = 11b, CLKXP = 0^{1+} (see Figure 37)

				-200				
NO.		PARAMETER			SL	UNIT		
			MIN	MAX	MIN	MAX		
1	t _{h(CKXL-FXL)}	Hold time, FSX low after CLKX low [¶]	L - 2	L + 3			ns	
2	t _{d(FXL-CKXH)}	Delay time, FSX low to CLKX high [#]	T - 2	T + 3			ns	
3	t _{d(CKXL-DXV)}	Delay time, CLKX low to DX valid	-2	4	3P + 4	5P + 17	ns	
6	t _{dis(CKXL-DXHZ)}	Disable time, DX high impedance following last data bit from CLKX low	-2	4	3P + 3	5P + 17	ns	
7	t _{d(FXL-DXV)}	Delay time, FSX low to DX valid	H - 2	H + 4	2P + 2	4P + 17	ns	

[†] P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

[‡] For all SPI slave modes, CLKG is programmed as 1/2 of the CPU clock by setting CLKSM = CLKGDV = 1.

§ S = sample rate generator input clock = P if CLKSM = 1 (P = 1/CPU clock frequency)

= sample rate generator input clock = P_clks if CLKSM = 0 (P_clks = CLKS period)

T = CLKX period = (1 + CLKGDV) * S

H = CLKX high pulse width = (CLKGDV/2 + 1) * S if CLKGDV is even

= (CLKGDV + 1)/2 * S if CLKGDV is odd or zero

- L = CLKX low pulse width = (CLKGDV/2) * S if CLKGDV is even
 - = (CLKGDV + 1)/2 * S if CLKGDV is odd or zero

¹ FSRP = FSXP = 1. As a SPI master, FSX is inverted to provide active-low slave-enable output. As a slave, the active-low signal input on FSX and FSR is inverted before being used internally.

CLKXM = FSXM = 1, CLKRM = FSRM = 0 for master McBSP

CLKXM = CLKRM = FSXM = FSRM = 0 for slave McBSP

[#] FSX should be low before the rising edge of clock to enable slave devices and then begin a SPI transfer at the rising edge of the master clock (CLKX).



SPRS051H - JANUARY 1997 - REVISED MARCH 2004









SPRS051H - JANUARY 1997 - REVISED MARCH 2004

MULTICHANNEL BUFFERED SERIAL PORT TIMING (CONTINUED)

timing requirements for McBSP as SPI master or slave: CLKSTP = 10b, CLKXP = 1^{+‡} (see Figure 38)

				-2	200		
NO.			MAS	TER	SLA	٧E	UNIT
			MIN	MAX	MIN	MAX	
4	t _{su(DRV-CKXH)}	Setup time, DR valid before CLKX high	12		2 - 3P		ns
5	t _{h(CKXH-DRV)}	Hold time, DR valid after CLKX high	4		5 + 6P		ns

[†] P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

[‡] For all SPI slave modes, CLKG is programmed as 1/2 of the CPU clock by setting CLKSM = CLKGDV = 1.

switching characteristics over recommended operating conditions for McBSP as SPI master or slave: CLKSTP = 10b, CLKXP = $1^{\dagger \ddagger}$ (see Figure 38)

NO.		PARAMETER	MAS	TER§	SLAVE		UNIT
			MIN	MAX	MIN	MAX	
1	t _{h(CKXH-FXL)}	Hold time, FSX low after CLKX high [¶]	T - 2	T + 3			ns
2	t _{d(FXL-CKXL)}	Delay time, FSX low to CLKX low [#]	H - 2	H + 3			ns
3	t _{d(CKXL-DXV)}	Delay time, CLKX low to DX valid	-2	4	3P + 4	5P + 17	ns
6	t _{dis(CKXH-DXHZ)}	Disable time, DX high impedance following last data bit from CLKX high	H - 2	H + 3			ns
7	t _{dis(FXH-DXHZ)}	Disable time, DX high impedance following last data bit from FSX high			P + 3	3P + 17	ns
8	t _{d(FXL-DXV)}	Delay time, FSX low to DX valid			2P + 2	4P + 17	ns

[†] P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

[‡] For all SPI slave modes, CLKG is programmed as 1/2 of the CPU clock by setting CLKSM = CLKGDV = 1.

S = sample rate generator input clock = P if CLKSM = 1 (P = 1/CPU clock frequency)

= sample rate generator input clock = P_clks if CLKSM = 0 (P_clks = CLKS period)

T = CLKX period = (1 + CLKGDV) * S

L = CLKX low pulse width

H = CLKX high pulse width = (CLKGDV/2 + 1) * S if CLKGDV is even

= (CLKGDV + 1)/2 * S if CLKGDV is odd or zero

= (CLKGDV + 1)/2 * S if CLKGDV is odd or zero

[¶] FSRP = FSXP = 1. As a SPI master, FSX is inverted to provide active-low slave-enable output. As a slave, the active-low signal input on FSX and FSR is inverted before being used internally.

CLKXM = FSXM = 1, CLKRM = FSRM = 0 for master McBSP

CLKXM = CLKRM = FSXM = FSRM = 0 for slave McBSP

[#] FSX should be low before the rising edge of clock to enable slave devices and then begin a SPI transfer at the rising edge of the master clock (CLKX).



Figure 38. McBSP Timing as SPI Master or Slave: CLKSTP = 10b, CLKXP = 1



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

MULTICHANNEL BUFFERED SERIAL PORT TIMING (CONTINUED)

timing requirements for McBSP as SPI master or slave: CLKSTP = 11b, CLKXP = 1^{+‡} (see Figure 39)

				-2	200		
NO.			MAS	TER	SLA	VE	UNIT
			MIN	MAX	MIN	MAX	
4	t _{su(DRV-CKXL)}	Setup time, DR valid before CLKX low	12		2 - 3P		ns
5	t _{h(CKXL-DRV)}	Hold time, DR valid after CLKX low	4		5 + 6P		ns

 † P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

[‡] For all SPI slave modes, CLKG is programmed as 1/2 of the CPU clock by setting CLKSM = CLKGDV = 1.

switching characteristics over recommended operating conditions for McBSP as SPI master or slave: CLKSTP = 11b, CLKXP = $1^{\dagger \ddagger}$ (see Figure 39)

NO.		PARAMETER	MAS	TER §	SLAVE		UNIT
			MIN	MAX	MIN	MAX	
1	t _{h(CKXH-FXL)}	Hold time, FSX low after CLKX high [¶]	H - 2	H + 3			ns
2	t _{d(FXL-CKXL)}	Delay time, FSX low to CLKX low [#]	T - 2	T + 1			ns
3	t _{d(CKXH-DXV)}	Delay time, CLKX high to DX valid	-2	4	3P + 4	5P + 17	ns
6	t _{dis(CKXH-DXHZ)}	Disable time, DX high impedance following last data bit from CLKX high	-2	4	3P + 3	5P + 17	ns
7	t _{d(FXL-DXV)}	Delay time, FSX low to DX valid	L - 2	L + 4	2P + 2	4P + 17	ns

[†] P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

[‡] For all SPI slave modes, CLKG is programmed as 1/2 of the CPU clock by setting CLKSM = CLKGDV = 1.

§ S = sample rate generator input clock = P if CLKSM = 1 (P = 1/CPU clock frequency)

= sample rate generator input clock = P_clks if CLKSM = 0 (P_clks = CLKS period)

T = CLKX period = (1 + CLKGDV) * S

H = CLKX high pulse width = (CLKGDV/2 + 1) * S if CLKGDV is even

= (CLKGDV + 1)/2 * S if CLKGDV is odd or zero

- L = CLKX low pulse width = (CLKGDV/2) * S if CLKGDV is even
 - = (CLKGDV + 1)/2 * S if CLKGDV is odd or zero

¹ FSRP = FSXP = 1. As a SPI master, FSX is inverted to provide active-low slave-enable output. As a slave, the active-low signal input on FSX and FSR is inverted before being used internally.

CLKXM = FSXM = 1, CLKRM = FSRM = 0 for master McBSP

CLKXM = CLKRM = FSXM = FSRM = 0 for slave McBSP

[#] FSX should be low before the rising edge of clock to enable slave devices and then begin a SPI transfer at the rising edge of the master clock (CLKX).



SPRS051H - JANUARY 1997 - REVISED MARCH 2004









SPRS051H - JANUARY 1997 - REVISED MARCH 2004

DMAC, TIMER, POWER-DOWN TIMING

switching characteristics over recommended operating conditions for DMAC outputs (see Figure 40)



Figure 40. DMAC Timing

timing requirements for timer inputs[†] (see Figure 41)

		-20	0	
NU.		MIN	MAX	UNIT
1	t _{w(TINP)} Pulse duration, TINP high or low	2P		ns
L				

[†] P = 1/CPU clock frequency in ns. For example, when running parts at 200 MHz, use P = 5 ns.

switching characteristics over recommended operating conditions for timer outputs (see Figure 41)



Figure 41. Timer Timing

switching characteristics over recommended operating conditions for power-down outputs (see Figure 42)

	DADAMETED			
	PARAMETER MI	MIN	MAX	UNIT
1 t _{d(CK01H-PDV)} Delay time, CLKOUT1 high to PD valid 2 9	O1H-PDV) Delay time, CLKOUT1 high to PD valid	2	9	ns
		~	/	





SPRS051H - JANUARY 1997 - REVISED MARCH 2004

JTAG TEST-PORT TIMING

timing requirements for JTAG test port (see Figure 43)

			-20	00	
NO.			MIN	MAX	UNIT
1	t _{c(TCK)}	Cycle time, TCK	35		ns
3	t _{su(TDIV-TCKH)}	Setup time, TDI/TMS/TRST valid before TCK high	10		ns
4	t _{h(TCKH-TDIV)}	Hold time, TDI/TMS/TRST valid after TCK high	9		ns

switching characteristics over recommended operating conditions for JTAG test port (see Figure 43)

NO	DADAMETED	-20		
NO.	PARAMETER	MIN	MAX	UNIT
2	t _{d(TCKL-TDOV)} Delay time, TCK low to TDO valid	-3	12	ns







SPRS051H - JANUARY 1997 - REVISED MARCH 2004

REVISION HISTORY

This data sheet revision history highlights the technical changes made to the SPR051G device-specific data sheet to make it an SPRS051H revision.

Scope: Applicable updates to the C62x device family, specifically relating to the C6201 device, have been incorporated.

PAGE(S) NO.	ADDITIONS/CHANGES/DELETIONS
All	Updated the title for literature number SPRU190 to: TMS320C6000 DSP Peripherals Overview Reference Guide
25	Added the power-down mode logic section and accompanying information.



SPRS051H - JANUARY 1997 - REVISED MARCH 2004

THERMAL/MECHANICAL DATA

The mechanical package diagrams that follow the tables reflect the most current released mechanical data available for the designated devices.

thermal resistance characteristics for GJC-352 package (S-PBGA package)

NO			°C/W	Air Flow LFPM [†]
1	$R\Theta_{JC}$	Junction-to-case	0.74	N/A
2	$R\Theta_{JA}$	Junction-to-free air	11.31	0
3	$R\Theta_{JA}$	Junction-to-free air	9.60	100
4	$R\Theta_{JA}$	Junction-to-free air	8.34	250
5	$R\Theta_{JA}$	Junction-to-free air	7.30	500

[†] LFPM = Linear Feet Per Minute

thermal resistance characteristics for GJL-352 (S-PBGA package)

NO		°C/W	Air Flow LFPM [†]
1	RΘ _{JC} Junction-to-case	0.47	N/A
2	RΘ _{JA} Junction-to-free air	14.2	0
3	RΘ _{JA} Junction-to-free air	12.3	100
4	RΘ _{JA} Junction-to-free air	10.2	250
5	$R\Theta_{JA}$ Junction-to-free air	8.6	500

[†] LFPM = Linear Feet Per Minute





www.ti.com

PACKAGING INFORMATION

Orderable Device	Status ⁽¹⁾	Package Type	Package Drawing	Pins	Package Qty	Eco Plan ⁽²⁾	Lead/ Ball Finish	MSL Peak Temp ⁽³⁾	Samples (Requires Login)
TMS320C6201GGP167	OBSOLETE	BGA	GGP	352		TBD	Call TI	Call TI	
TMS320C6201GGP200	OBSOLETE	BGA	GGP	352		TBD	Call TI	Call TI	
TMS320C6201GJC200	ACTIVE	FCBGA	GJC	352	21	TBD	SNPB	Level-4-220C-72 HR	
TMS320C6201GJCA200	ACTIVE	FCBGA	GJC	352	21	TBD	SNPB	Level-4-220C-72 HR	
TMS320C6201GJL200	ACTIVE	FCBGA	GJL	352	40	TBD	SNPB	Level-4-220C-72 HR	
TMS320C6201GJLA200	ACTIVE	FCBGA	GJL	352	1	TBD	SNPB	Level-4-220C-72 HR	
TMX320C6201BGJL	OBSOLETE	FCBGA	GJL	352		TBD	Call TI	Call TI	

⁽¹⁾ The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSOLETE: TI has discontinued the production of the device.

⁽²⁾ Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

⁽³⁾ MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

OTHER QUALIFIED VERSIONS OF TMS320C6201 :





www.ti.com

9-Aug-2012

• Enhanced Product: SM320C6201-EP

Military: SMJ320C6201

NOTE: Qualified Version Definitions:

- Enhanced Product Supports Defense, Aerospace and Medical Applications
- Military QML certified for Military and Defense Applications

MECHANICAL DATA

MPBG018A - OCTOBER 1996 - REVISED JANUARY 2002

PLASTIC BALL GRID ARRAY (CAVITY DOWN)



NOTES: A. All linear dimensions are in millimeters.

GGP (S-PBGA-N352)

B. This drawing is subject to change without notice.

C. Thermally enhanced plastic package with metal heat slug (HSL)



MPBG067B - SEPTEMBER 1998 - REVISED JANUARY 2002

PLASTIC BALL GRID ARRAY

GJC (S-PBGA-N352)



NOTES: A. All linear dimensions are in millimeters.

- B. This drawing is subject to change without notice.
- C. Thermally enhanced plastic package with heat slug (HSL).
- D. Flip chip application only
- E. Possible protrusion in this area, but within 3,50 max package height specification
- F. Falls within JEDEC MO-151/BAR-2



MPBG069D - SEPTEMBER 1998 - REVISED MARCH 2002

GJL (S-PBGA-N352)

PLASTIC BALL GRID ARRAY



NOTES: A. All linear dimensions are in millimeters.

- B. This drawing is subject to change without notice.
- C. Thermally enhanced plastic package with heat slug (HSL)
- D. Flip chip application only
- E. Possible protrusion in this area, but within 3,50 max package height specification
- F. Falls within JEDEC MO-151/AAL-1



IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46C and to discontinue any product or service per JESD48B. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have *not* been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components which meet ISO/TS16949 requirements, mainly for automotive use. Components which have not been so designated are neither designed nor intended for automotive use; and TI will not be responsible for any failure of such components to meet such requirements.

	Applications	
www.ti.com/audio	Automotive and Transportation	www.ti.com/automotive
amplifier.ti.com	Communications and Telecom	www.ti.com/communications
dataconverter.ti.com	Computers and Peripherals	www.ti.com/computers
www.dlp.com	Consumer Electronics	www.ti.com/consumer-apps
dsp.ti.com	Energy and Lighting	www.ti.com/energy
www.ti.com/clocks	Industrial	www.ti.com/industrial
interface.ti.com	Medical	www.ti.com/medical
logic.ti.com	Security	www.ti.com/security
power.ti.com	Space, Avionics and Defense	www.ti.com/space-avionics-defense
microcontroller.ti.com	Video and Imaging	www.ti.com/video
www.ti-rfid.com		
www.ti.com/omap	TI E2E Community	e2e.ti.com
www.ti.com/wirelessconnectivity		
	www.ti.com/audio amplifier.ti.com dataconverter.ti.com www.dlp.com dsp.ti.com dsp.ti.com www.ti.com/clocks interface.ti.com logic.ti.com power.ti.com microcontroller.ti.com www.ti-rfid.com www.ti-rfid.com www.ti.com/omap www.ti.com/wirelessconnectivity	Applicationswww.ti.com/audioAutomotive and Transportationamplifier.ti.comCommunications and Telecomdataconverter.ti.comComputers and Peripheralswww.dlp.comConsumer Electronicsdsp.ti.comEnergy and Lightingwww.ti.com/clocksIndustrialinterface.ti.comMedicallogic.ti.comSpace, Avionics and Defensemicrocontroller.ti.comVideo and Imagingwww.ti-rfid.comTI E2E Communitywww.ti.com/wirelessconnectivityKet State

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2012, Texas Instruments Incorporated