

NE/SE5539 Ultra-High Frequency Operational Amplifier

Product Specification

Linear Products

DESCRIPTION

The NE/SE5539 is a very wide bandwidth, high slew rate, monolithic operational amplifier for use in video amplifiers, RF amplifiers, and extremely high slew rate amplifiers.

Emitter-follower inputs provide a true differential high input impedance device. Proper external compensation will allow design operation over a wide range of closed-loop gains, both inverting and non-inverting, to meet specific design requirements.


FEATURES

- Gain bandwidth product: 1.2GHz at 17dB
- Slew rate: 600/V μ s
- Full power response: 48MHz
- A_{vol}: 52dB typical
- 350MHz unity gain

APPLICATIONS

- Fast pulse amplifiers
- RF oscillators
- Fast sample and hold
- High gain video amplifiers (BW > 20MHz)

PIN CONFIGURATION



ORDERING INFORMATION

DESCRIPTION	TEMPERATURE RANGE	ORDER CODE
14-Pin Plastic DIP	0 to +70°C	NE5539N
14-Pin Plastic SO	0 to +70°C	NE5539D
14-Pin Cerdip	0 to +70°C	NE5539F
14-Pin Plastic DIP	-55°C to +125°C	SE5539N
14-Pin Cerdip	-55°C to +125°C	SE5539F

ABSOLUTE MAXIMUM RATINGS¹

SYMBOL	PARAMETER	RATING	UNIT
V _{CC}	Supply voltage	± 12	V
P _D	Internal power dissipation	550	mW
T _{STG}	Storage temperature range	-65 to +150	°C
T _J	Max junction temperature	150	°C
T _A	Operating temperature range	0 to 70 -55 to +125	°C °C
T _{SOLD}	Lead temperature (10sec max)	300	°C


NOTE:

1. Differential input voltage should not exceed 0.25V to prevent excessive input bias current and common-mode voltage 2.5V. These voltage limits may be exceeded if current is limited to less than 10mA.

Ultra-High Frequency Operational Amplifier

NE/SE5539

EQUIVALENT CIRCUIT

DC ELECTRICAL CHARACTERISTICS $V_{CC} = \pm 8V$, $T_A = 25^\circ C$, unless otherwise specified.

SYMBOL	PARAMETER	TEST CONDITIONS	SE5539			NE5539			UNIT
			Min	Typ	Max	Min	Typ	Max	
V_{OS}	Input offset voltage	$V_O = 0V$, $R_S = 100\Omega$	Over temp	2	5				mV
			$T_A = 25^\circ C$	2	3		2.5	5	
	$\Delta V_{OS}/\Delta T$			5			5		$\mu V/^\circ C$
I_{OS}	Input offset current		Over temp	0.1	3				μA
			$T_A = 25^\circ C$	0.1	1			2	
	$\Delta I_{OS}/\Delta T$			0.5			0.5		$nA/^\circ C$
I_B	Input bias current		Over temp	6	25				μA
			$T_A = 25^\circ C$	5	13		5	20	
	$\Delta I_B/\Delta T$			10			10		$nA/^\circ C$
CMRR	Common-mode rejection ratio	$F = 1kHz$, $R_S = 100\Omega$, $V_{CM} \pm 1.7V$	70	80		70	80		dB
			Over temp	70	80				
R_{IN}	Input impedance			100			100		$k\Omega$
R_{OUT}	Output impedance			10			10		Ω

Ultra-High Frequency Operational Amplifier

NE/SE5539

DC ELECTRICAL CHARACTERISTICS (Continued) $V_{CC} = \pm 8V$, $T_A = 25^\circ C$, unless otherwise specified.

SYMBOL	PARAMETER	TEST CONDITIONS	SE5539			NE5539			UNIT
			Min	Typ	Max	Min	Typ	Max	
V_{OUT}	Output voltage swing	$R_L = 150\Omega$ to GND and 470Ω to $-V_{CC}$	+ Swing			+2.3	+2.7		V
			- Swing			-1.7	-2.2		
V_{OUT}	Output voltage swing	$R_L = 2k\Omega$ to GND	Over temp	+ Swing	+2.3	+3.0			V
				- Swing	-1.5	-2.1			
		$T_A = 25^\circ C$		+ Swing	+2.5	+3.1			V
				- Swing	-2.0	-2.7			
I_{CC+}	Positive supply current	$V_0 = 0$, $R_1 = \infty$	Over temp		14	18			mA
			$T_A = 25^\circ C$		14	17		14 18	
I_{CC-}	Negative supply current	$V_0 = 0$, $R_1 = \infty$	Over temp		11	15			mA
			$T_A = 25^\circ C$		11	14		11 15	
PSRR	Power supply rejection ratio	$\Delta V_{CC} = \pm 1V$	Over temp		300	1000			$\mu V/V$
			$T_A = 25^\circ C$					200 1000	
A_{VOL}	Large signal voltage gain	$V_0 = +2.3V$, $-1.7V$ $R_L = 150\Omega$ to GND, 470Ω to $-V_{CC}$				47	52	57	dB
A_{VOL}	Large signal voltage gain	$V_0 = +2.3V$, $-1.7V$ $R_L = 2\Omega$ to GND							dB
		$T_A = 25^\circ C$				47	52	57	
A_{VOL}	Large signal voltage gain	$V_0 = +2.5V$, $-2.0V$ $R_L = 2k\Omega$ to GND	Over temp	46		60			dB
			$T_A = 25^\circ C$	48	53	58			

DC ELECTRICAL CHARACTERISTICS $V_{CC} = \pm 6V$, $T_A = 25^\circ C$, unless otherwise specified.

SYMBOL	PARAMETER	TEST CONDITIONS		SE5539			UNIT
				Min	Typ	Max	
V _{OS}	Input offset voltage		Over temp		2	5	mV
			T _A = 25°C		2	3	
I _{OS}	Input offset current		Over temp		0.1	3	μA
			T _A = 25°C		0.1	1	
I _B	Input bias current		Over temp		5	20	μA
			T _A = 25°C		4	10	
CMRR	Common-mode rejection ratio	V _{CM} = ± 1.3V, R _S = 100Ω		70	85		dB
I _{CC} +	Positive supply current		Over temp		11	14	mA
			T _A = 25°C		11	13	
I _{CC} -	Negative supply current		Over temp		8	11	mA
			T _A = 25°C		8	10	
PSRR	Power supply rejection ratio	ΔV _{CC} = ± 1V	Over temp		300	1000	μV/V
			T _A = 25°C				
V _{OUT}	Output voltage swing	R _L = 150Ω to GND and 390Ω to -V _{CC}	Over temp	+ Swing	+1.4	+2.0	V
				- Swing	-1.1	-1.7	
			T _A = 25°C	+ Swing	+1.5	+2.0	
				- Swing	-1.4	-1.8	

Ultra-High Frequency Operational Amplifier

NE/SE5539

AC ELECTRICAL CHARACTERISTICS $V_{CC} = \pm 8V$, $R_L = 150\Omega$ to GND & 470Ω to $-V_{CC}$, unless otherwise specified.

SYMBOL	PARAMETER	TEST CONDITIONS	SE5539			NE5539			UNIT
			Min	Typ	Max	Min	Typ	Max	
BW	Gain bandwidth product	$A_{CL} = 7$, $V_O = 0.1 V_{P-P}$		1200			1200		MHz
	Small-signal bandwidth	$A_{CL} = 2$, $R_L = 150\Omega^1$		110			110		MHz
t_s	Settling time	$A_{CL} = 2$, $R_L = 150\Omega^1$		15			15		ns
SR	Slew rate	$A_{CL} = 2$, $R_L = 150\Omega^1$		600			600		V/ μs
t_{PD}	Propagation delay	$A_{CL} = 2$, $R_L = 150\Omega^1$		7			7		ns
	Full power response	$A_{CL} = 2$, $R_L = 150\Omega^1$		48			48		MHz
	Full power response	$A_V = 7$, $R_L = 150\Omega^1$		20			20		MHz
	Input noise voltage	$R_S = 50\Omega$		4			4		nV/ $\sqrt{Hz}$


NOTE:
1. External compensation.

AC ELECTRICAL CHARACTERISTICS $V_{CC} = \pm 6V$, $R_L = 150\Omega$ to GND and 390Ω to $-V_{CC}$, unless otherwise specified.

SYMBOL	PARAMETER	TEST CONDITIONS	SE5539			UNIT
			Min	Typ	Max	
BW	Gain bandwidth product	$A_{CL} = 7$		700		MHz
	Small-signal bandwidth	$A_{CL} = 2^1$		120		MHz
t_s	Settling time	$A_{CL} = 2^1$		23		ns
SR	Slew rate	$A_{CL} = 2^1$		330		V/ μs
t_{PD}	Propagation delay	$A_{CL} = 2^1$		4.5		ns
	Full power response	$A_{CL} = 2^1$		20		MHz

NOTE:
1. External compensation.

TYPICAL PERFORMANCE CURVES




Ultra-High Frequency Operational Amplifier

NE/SE5539


TYPICAL PERFORMANCE CURVES (Continued)

Power Bandwidth (SE)




OP052055

Power Bandwidth (NE)




OP052105

SE5539 Open-Loop Gain vs Frequency




OP052205

Power Bandwidth




OP062305

SE5539 Open-Loop Phase vs Frequency



Gain Bandwidth Product vs Frequency



OP062505

NOTE

Indicates typical distribution $-55^{\circ}\text{C} \leq T_A \leq 125^{\circ}\text{C}$

OP062405

Ultra-High Frequency Operational Amplifier


NE/SE5539

CIRCUIT LAYOUT
CONSIDERATIONS

As may be expected for an ultra-high frequency, wide gain bandwidth amplifier, the physi-

cal circuit layout is extremely critical. Breadboarding is not recommended. A double-sided copper-clad printed circuit board will result in more favorable system operation. An

example utilizing a 28dB non-inverting amp is shown in Figure 1.



TD06740B

NOTES:


$R_1 = 75\Omega$ 5% CARBON
 $R_2 = 75\Omega$ 5% CARBON
 $R_3 = 75\Omega$ 5% CARBON
 $R_4 = 36k$ 5% CARBON

$R_5 = 20k$ TRIMPOT (CERMET)
 $R_F = 1.5k$ (28dB GAIN)
 $R_6 = 470\Omega$ 5% CARBON

RFC 3T # 26 BUSSWIRE ON
 FERROXCUBE VK 200 09/3B CORE
 BYPASS CAPACITORS
 1nF CERAMIC
 (MEPCO OR EQUIV.)

Top Plane Copper¹
(Component Side)


DF059103

Component Side
(Component Layout)

DF059205

NOTES:

(X) indicates ground connection to top plane.
¹ R_6 is on bottom side.

Bottom Plane
Copper¹

DF059305

NOTE:

Bond edges of top and bottom ground plane copper.

Figure 1. 28dB Non-Inverting Amp Sample PC Layout

Ultra-High Frequency Operational Amplifier

NE/SE5539

NE5539 COLOR VIDEO AMPLIFIER

The NE5539 wideband operational amplifier is easily adapted for use as a color video amplifier. A typical circuit is shown in Figure 2 along with vector-scope¹ photographs showing the amplifier differential gain and phase response to a standard five-step modulated staircase linearity signal (Figures 3, 4 and 5). As can be seen in Figure 4, the gain varies less than 0.5% from the bottom to the top of the staircase. The maximum differential phase shown in Figure 5 is approximately $\pm 0.1^\circ$.

The amplifier circuit was optimized for a 75Ω input and output termination impedance with a gain of approximately 10 (20dB).

NOTE:

1. The input signal was 200mV and the output 2V.
V_{CC} was $\pm 8V$.




Figure 2. NE5539 Video Amplifier




Figure 3. Input Signal





Figure 4. Differential Gain < 0.5%

NOTE:

1. Instruments used for these measurements were Tektronix, 146 NTSC test signal generator, 520A NTSC vectorscope, and 1480 waveform monitor.

Ultra-High Frequency Operational Amplifier

NE/SE5539

Figure 5. Differential Phase $+0.1^\circ$

APPLICATIONS




Figure 6. Non-Inverting Follower




Figure 7. Inverting Follower