

New Jersey Semi-Conductor Products, Inc.

20 STERN AVE.
SPRINGFIELD, NEW JERSEY 07081
U.S.A.

TELEPHONE: (973) 376-2922
(212) 227-6005
FAX: (973) 376-8960

NPN POWER SILICON SWITCHING TRANSISTOR

2N5339


MAXIMUM RATINGS

Ratings	Symbol	Value	Units
Collector-Emitter Voltage	V_{CEO}	100	Vdc
Collector-Base Voltage	V_{CBO}	100	Vdc
Emitter-Base Voltage	V_{EBO}	6.0	Vdc
Base Current	I_B	1.0	Adc
Collector Current	I_C	5.0	Adc
Total Power Dissipation (@ $T_A = +25^\circ\text{C}$) (@ $T_c = +25^\circ\text{C}$)	P_T	1.0 10	W W
Operating & Storage Junction Temperature Range	T_{op}, T_{stg}	-55 to +200	$^\circ\text{C}$

THERMAL CHARACTERISTICS

Characteristics	Symbol	Max.	Unit
Thermal Resistance, Junction-to-Case	$R_{\theta JC}$	17.5	$^\circ\text{C/W}$

- 1) Derate linearly 5.71 mW/ $^\circ\text{C}$ for $T_A > 25^\circ\text{C}$
 2) Derate linearly 57.1 mW/ $^\circ\text{C}$ for $T_c > 25^\circ\text{C}$




*See appendix A for
package outline

ELECTRICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$ unless otherwise noted)

Characteristics	Symbol	Min.	Max.	Unit
OFF CHARACTERISTICS				
Collector-Emitter Breakdown Voltage $I_C = 50 \mu\text{Adc}$	$V_{(BR)CEO}$	100		Vdc
Collector-Emitter Cutoff Current $V_{CE} = 100 \text{ Vdc}$	I_{CEO}		100	μAdc
Collector-Emitter Cutoff Current $V_{CE} = 90 \text{ Vdc}, V_{BE} = 1.5 \text{ Vdc}$	I_{CEX}		10	μAdc
Collector-Base Cutoff Current $V_{CB} = 100 \text{ Vdc}$	I_{CBO}		10	μAdc
Emitter-Base Cutoff Current $V_{EB} = 6.0 \text{ Vdc}$	I_{EBO}		100	μAdc

NJ Semi-Conductors reserves the right to change test conditions, parameters limits and package dimensions without notice information furnished by NJ Semi-Conductors is believed to be both accurate and reliable at the time of going to press. However NJ Semi-Conductors assumes no responsibility for any errors or omissions discovered in its use. NJ Semi-Conductors encourages customers to verify that datasheets are current before placing orders.

Quality Semi-Conductors



ELECTRICAL CHARACTERISTICS (con't)

Characteristics	Symbol	Min.	Max.	Unit
ON CHARACTERISTICS⁽³⁾				
Forward-Current Transfer Ratio $I_C = 0.5 \text{ Adc}, V_{CE} = 2.0 \text{ Vdc}$ $I_C = 2.0 \text{ Adc}, V_{CE} = 2.0 \text{ Vdc}$ $I_C = 5.0 \text{ Adc}, V_{CE} = 2.0 \text{ Vdc}$	h_{FE}	60 60 40	240	
Collector-Emitter Saturation Voltage $I_C = 2.0 \text{ Adc}, I_B = 0.2 \text{ Adc}$ $I_C = 5.0 \text{ Adc}, I_B = 0.5 \text{ Adc}$	$V_{CE(sat)}$		0.7 1.2	Vdc
Base-Emitter Saturation Voltage $I_C = 2.0 \text{ Adc}, I_B = 0.2 \text{ Adc}$ $I_C = 5.0 \text{ Adc}, I_B = 0.5 \text{ Adc}$	$V_{BE(sat)}$		1.2 1.8	Vdc

DYNAMIC CHARACTERISTICS

Magnitude of Common Emitter Small-Signal Short-Circuit Forward Current Transfer Ratio $I_C = 0.5 \text{ Adc}, V_{CE} = 10 \text{ Vdc}, f = 10 \text{ MHz}$	$ h_{fe} $	3.0	15	
Output Capacitance $V_{CB} = 10 \text{ Vdc}, I_E = 0, 100 \text{ kHz} \leq f \leq 1.0 \text{ MHz}$	C_{obo}		250	pF
Input Capacitance $V_{BE} = 2.0 \text{ Vdc}, I_E = 0, 100 \text{ kHz} \leq f \leq 1.0 \text{ MHz}$	C_{ibo}		1.000	pF

SAFE OPERATING AREA

DC Tests $T_C = \pm 25^\circ\text{C}, 1 \text{ Cycle}, t \geq 0.5 \text{ s}$
Test 1 $V_{CE} = 2.0 \text{ Vdc}, I_C = 5.0 \text{ Adc}$
Test 2 $V_{CE} = 5.0 \text{ Vdc}, I_C = 2.0 \text{ Adc}$
Test 3 $V_{CE} = 90 \text{ Vdc}, I_C = 55 \text{ mAdc}$

(3) Pulse Test: Pulse Width = 300μs, Duty Cycle ≤ 2.0%.